

REPLACEMENT PART LIST

The components which are referred positions may changes by model, size, cosmetic and specification of the LCD TV.
Please apply web pages for current part list. The items marked with red are safety components or need to be replaced with original/approved parts.

POS	PART NUMBER	PART DESCRIPTION	POS	PART NUMBER	PART DESCRIPTION
X941	032150R	HP JACK 17"LCD TV (OLD-8R9185)	R217	172479R	RC-CHIP 4.7K J 1/16W /0603 TAPE
X940	031224R	CONN.HOUS.3P 2317-3S JST B 3B-XH-A WHITE	R222	172479R	RC-CHIP 4.7K J 1/16W /0603 TAPE
	Y10184	H.PHONE MOD-PN LCD TV L5A CHASIS	R213	172479R	RC-CHIP 4.7K J 1/16W /0603 TAPE
C940	273471R	C-PEM 47NF K 63V R:5	R406	170474R	RC-CHIP 47R J 1/16W /0603 TAPE
C941	273471R	C-PEM 47NF K 63V R:5	R407	170474R	RC-CHIP 47R J 1/16W /0603 TAPE
	Y10187R	R/C L5A SASI KUMANDA KMK-01 SILVER	R408	170474R	RC-CHIP 47R J 1/16W /0603 TAPE
	N1F110	LC SD-32W M/NX/2/K/SV/VGA/A-OSD/AU3	R409	170474R	RC-CHIP 47R J 1/16W /0603 TAPE
C639	252482R	EC 470UF 16V 12.5*10 R:5	R410	170474R	RC-CHIP 47R J 1/16W /0603 TAPE
U605	452904R	IC LM78L08ACZ	R411	170474R	RC-CHIP 47R J 1/16W /0603 TAPE
Y300	056161R	CRYSTAL 20.25MHZ HC49-U	U402	458931R	IC-CHIP PI3V512 RGB SW PERICOM
S300	031224R	CONN.HOUS.3P 2317-3S JST B 3B-XH-A WHITE	U402	450526R	IC-CHIP PI3V512QEX (QSOP24)
S301	031251R	SCART SOCKET 14.1	D301	303818R	DIODE-CHIP BAV99LT1 SOT23 T&R
Y200	056119R	CRYSTAL 14.31818MHz CL=18PF30/30PPMHC49U	Q200	401472R	TRN-CHIP 2N7002 N-CHANNEL SOT23
SW201	010844R	TACT SWITCH 2 LEG (MTSB)	Q201	401472R	TRN-CHIP 2N7002 N-CHANNEL SOT23
J310	031163R	KONN. CINCH WHITE HOR.14.1	R363	170754R	RC-CHIP 75R J 1/16W /0603
J309	031164R	KONN. CINCH RED HOR.14.1	R365	170754R	RC-CHIP 75R J 1/16W /0603
L200	053352R	COIL- CHOKE 10UH R0814 14.1	R366	170754R	RC-CHIP 75R J 1/16W /0603
L202	053352R	COIL- CHOKE 10UH R0814 14.1	R367	170754R	RC-CHIP 75R J 1/16W /0603
L300	053352R	COIL- CHOKE 10UH R0814 14.1	R368	170754R	RC-CHIP 75R J 1/16W /0603
L301	053352R	COIL- CHOKE 10UH R0814 14.1	R369	170754R	RC-CHIP 75R J 1/16W /0603
L312	053352R	COIL- CHOKE 10UH R0814 14.1	R415	170754R	RC-CHIP 75R J 1/16W /0603
S204	031194R	CONN.HOUS.4P 2317-4S JST B 4B-XH-A WHITE	R416	170754R	RC-CHIP 75R J 1/16W /0603
S202	031194R	CONN.HOUS.4P 2317-4S JST B 4B-XH-A WHITE	R417	170754R	RC-CHIP 75R J 1/16W /0603
SAW300	056298R	SAW FILTER X6966M	C413	290223R	CC-CHIP 22PF J 50V /0603 NPO TAPE
U303	S-SWVCTI01BG	SW IC VCTI 5LC BEKO/GRUNDIG	C414	290223R	CC-CHIP 22PF J 50V /0603 NPO TAPE
U303	S-SWVCTI01BGV	SW IC VCTI 5LC BEKO/GRUNDIG VD	R235	171107R	RC-CHIP 100R J 1/16W /0603
C629	253128R	EC 1000UF 16V 20*10 R:5 LOW ESR	R236	171107R	RC-CHIP 100R J 1/16W /0603
P400	031358R	CONN. VGA B10B	R341	171107R	RC-CHIP 100R J 1/16W /0603
R237	171250R	RC-CHIP 249R F %1 / 0603	R342	171107R	RC-CHIP 100R J 1/16W /0603
U201	452662R-2	IC-CHIP AT24C16AN 10SU2.7 TAPE&REEL	R345	171107R	RC-CHIP 100R J 1/16W /0603
U300	452706R-1	IC TDA1308T/N2 SO-G8 (T&R)	R346	171107R	RC-CHIP 100R J 1/16W /0603
U200	453296R	IC-CHIP GM2221-LF-BC 208PIN PQFP TRAY	R257	171107R	RC-CHIP 100R J 1/16W /0603
R325	170225R	RC-CHIP 22R J 1/10W /0603	R255	171107R	RC-CHIP 100R J 1/16W /0603
C371	292114R	CC-CHIP 1NF K 50V /0603 X7R	R347	171107R	RC-CHIP 100R J 1/16W /0603
C372	292114R	CC-CHIP 1NF K 50V /0603 X7R	R348	171107R	RC-CHIP 100R J 1/16W /0603
C373	292114R	CC-CHIP 1NF K 50V /0603 X7R	R357	171107R	RC-CHIP 100R J 1/16W /0603
C376	292114R	CC-CHIP 1NF K 50V /0603 X7R	R358	172104R	RC-CHIP 1K J 1/16W /0603
C377	292114R	CC-CHIP 1NF K 50V /0603 X7R	R607	172104R	RC-CHIP 1K J 1/16W /0603
C378	292114R	CC-CHIP 1NF K 50V /0603 X7R	R258	172104R	RC-CHIP 1K J 1/16W /0603
C379	292114R	CC-CHIP 1NF K 50V /0603 X7R	R423	172104R	RC-CHIP 1K J 1/16W /0603
C380	292114R	CC-CHIP 1NF K 50V /0603 X7R	R424	172104R	RC-CHIP 1K J 1/16W /0603
C381	292114R	CC-CHIP 1NF K 50V /0603 X7R	R418	172104R	RC-CHIP 1K J 1/16W /0603
C390	292114R	CC-CHIP 1NF K 50V /0603 X7R	R419	172104R	RC-CHIP 1K J 1/16W /0603
C391	292114R	CC-CHIP 1NF K 50V /0603 X7R	C394	292153R	CC-CHIP 1.5NF K 50V /0603 X7R TAPE
C392	292114R	CC-CHIP 1NF K 50V /0603 X7R	C395	292153R	CC-CHIP 1.5NF K 50V /0603 X7R TAPE
C393	292114R	CC-CHIP 1NF K 50V /0603 X7R	R401	171336R	RC-CHIP 330R J 1/16W /0603 TAPE
J304	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE	R402	171336R	RC-CHIP 330R J 1/16W /0603 TAPE
J235	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE	R385	172513R	RC-CHIP 5.1K J 1/16W /0603
J305	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE	R378	172567R	RC-CHIP 5.6K J 1/16W /0603 TAPE
J314	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE	R379	172567R	RC-CHIP 5.6K J 1/16W /0603 TAPE
R422	172686R	RC-CHIP 6.8K J 1/16W /0603	C321	294125R	CC-CHIP 100NF K 25V /0603 X7R
R398	173277R	RC-CHIP 27K J 1/16W /0603 TAPE	C446	294125R	CC-CHIP 100NF K 25V /0603 X7R

POS	PART NUMBER	PART DESCRIPTION	POS	PART NUMBER	PART DESCRIPTION
C200	294125R	CC-CHIP 100NF K 25V /0603 X7R	C448	294125R	CC-CHIP 100NF K 25V /0603 X7R
C201	294125R	CC-CHIP 100NF K 25V /0603 X7R	C449	294125R	CC-CHIP 100NF K 25V /0603 X7R
C202	294125R	CC-CHIP 100NF K 25V /0603 X7R	C450	294125R	CC-CHIP 100NF K 25V /0603 X7R
C203	294125R	CC-CHIP 100NF K 25V /0603 X7R	C451	294125R	CC-CHIP 100NF K 25V /0603 X7R
C204	294125R	CC-CHIP 100NF K 25V /0603 X7R	C456	294125R	CC-CHIP 100NF K 25V /0603 X7R
C205	294125R	CC-CHIP 100NF K 25V /0603 X7R	C609	294125R	CC-CHIP 100NF K 25V /0603 X7R
C206	294125R	CC-CHIP 100NF K 25V /0603 X7R	C610	294125R	CC-CHIP 100NF K 25V /0603 X7R
C207	294125R	CC-CHIP 100NF K 25V /0603 X7R	C615	294125R	CC-CHIP 100NF K 25V /0603 X7R
C208	294125R	CC-CHIP 100NF K 25V /0603 X7R	C616	294125R	CC-CHIP 100NF K 25V /0603 X7R
C228	294125R	CC-CHIP 100NF K 25V /0603 X7R	C617	294125R	CC-CHIP 100NF K 25V /0603 X7R
C229	294125R	CC-CHIP 100NF K 25V /0603 X7R	C619	294125R	CC-CHIP 100NF K 25V /0603 X7R
C230	294125R	CC-CHIP 100NF K 25V /0603 X7R	C620	294125R	CC-CHIP 100NF K 25V /0603 X7R
C231	294125R	CC-CHIP 100NF K 25V /0603 X7R	C621	294125R	CC-CHIP 100NF K 25V /0603 X7R
C232	294125R	CC-CHIP 100NF K 25V /0603 X7R	C622	294125R	CC-CHIP 100NF K 25V /0603 X7R
C233	294125R	CC-CHIP 100NF K 25V /0603 X7R	C623	294125R	CC-CHIP 100NF K 25V /0603 X7R
C234	294125R	CC-CHIP 100NF K 25V /0603 X7R	C624	294125R	CC-CHIP 100NF K 25V /0603 X7R
C235	294125R	CC-CHIP 100NF K 25V /0603 X7R	C316	294125R	CC-CHIP 100NF K 25V /0603 X7R
C236	294125R	CC-CHIP 100NF K 25V /0603 X7R	C327	294125R	CC-CHIP 100NF K 25V /0603 X7R
C237	294125R	CC-CHIP 100NF K 25V /0603 X7R	C242	294125R	CC-CHIP 100NF K 25V /0603 X7R
C238	294125R	CC-CHIP 100NF K 25V /0603 X7R	C311	294125R	CC-CHIP 100NF K 25V /0603 X7R
C239	294125R	CC-CHIP 100NF K 25V /0603 X7R	C312	294125R	CC-CHIP 100NF K 25V /0603 X7R
C300	294125R	CC-CHIP 100NF K 25V /0603 X7R	R200	173100R	RC-CHIP 10K J 1/10W /0603
C301	294125R	CC-CHIP 100NF K 25V /0603 X7R	R201	173100R	RC-CHIP 10K J 1/10W /0603
C302	294125R	CC-CHIP 100NF K 25V /0603 X7R	R202	173100R	RC-CHIP 10K J 1/10W /0603
C303	294125R	CC-CHIP 100NF K 25V /0603 X7R	R203	173100R	RC-CHIP 10K J 1/10W /0603
C304	294125R	CC-CHIP 100NF K 25V /0603 X7R	R243	173100R	RC-CHIP 10K J 1/10W /0603
C305	294125R	CC-CHIP 100NF K 25V /0603 X7R	R245	173100R	RC-CHIP 10K J 1/10W /0603
C306	294125R	CC-CHIP 100NF K 25V /0603 X7R	R300	173100R	RC-CHIP 10K J 1/10W /0603
C307	294125R	CC-CHIP 100NF K 25V /0603 X7R	R302	173100R	RC-CHIP 10K J 1/10W /0603
C308	294125R	CC-CHIP 100NF K 25V /0603 X7R	R304	173100R	RC-CHIP 10K J 1/10W /0603
C309	294125R	CC-CHIP 100NF K 25V /0603 X7R	R322	173100R	RC-CHIP 10K J 1/10W /0603
C310	294125R	CC-CHIP 100NF K 25V /0603 X7R	R323	173100R	RC-CHIP 10K J 1/10W /0603
C313	294125R	CC-CHIP 100NF K 25V /0603 X7R	R334	173100R	RC-CHIP 10K J 1/10W /0603
C314	294125R	CC-CHIP 100NF K 25V /0603 X7R	R604	173100R	RC-CHIP 10K J 1/10W /0603
C315	294125R	CC-CHIP 100NF K 25V /0603 X7R	R247	173100R	RC-CHIP 10K J 1/10W /0603
C317	294125R	CC-CHIP 100NF K 25V /0603 X7R	R248	173100R	RC-CHIP 10K J 1/10W /0603
C318	294125R	CC-CHIP 100NF K 25V /0603 X7R	R249	173100R	RC-CHIP 10K J 1/10W /0603
C319	294125R	CC-CHIP 100NF K 25V /0603 X7R	R250	173100R	RC-CHIP 10K J 1/10W /0603
C463	293113R	CC-CHIP 10NF K 50V /0603 X7R	R227	173100R	RC-CHIP 10K J 1/10W /0603
C405	292229R	CC-CHIP 2.2NF J 50V/0603 NPO	R228	173100R	RC-CHIP 10K J 1/10W /0603
C406	292229R	CC-CHIP 2.2NF J 50V/0603 NPO	R229	173100R	RC-CHIP 10K J 1/10W /0603
C407	292229R	CC-CHIP 2.2NF J 50V/0603 NPO	R246	173100R	RC-CHIP 10K J 1/10W /0603
C408	292229R	CC-CHIP 2.2NF J 50V/0603 NPO	R256	173100R	RC-CHIP 10K J 1/10W /0603
C251	299501R	CC-CHIP 5PF J 50V /0603 NPO	R230	173100R	RC-CHIP 10K J 1/10W /0603
C252	299501R	CC-CHIP 5PF J 50V /0603 NPO	R231	173100R	RC-CHIP 10K J 1/10W /0603
U604	401372R	TRN FDS9933A	R273	173100R	RC-CHIP 10K J 1/10W /0603
C243	291226R	CC-CHIP 220PF J 50V /0603 NPO TAPE	R386	173100R	RC-CHIP 10K J 1/10W /0603
C244	291226R	CC-CHIP 220PF J 50V /0603 NPO TAPE	R361	173183R	RC-CHIP 18K J 1/16W /0603 TAPE
C245	291226R	CC-CHIP 220PF J 50V /0603 NPO TAPE	C253	293113R	CC-CHIP 10NF K 50V /0603 X7R
C246	291226R	CC-CHIP 220PF J 50V /0603 NPO TAPE	C330	293113R	CC-CHIP 10NF K 50V /0603 X7R
C337	291476R	CC-CHIP 470PF J 50V /0603 NP0 T&R	C331	293113R	CC-CHIP 10NF K 50V /0603 X7R
C338	291476R	CC-CHIP 470PF J 50V /0603 NP0 T&R	C457	293113R	CC-CHIP 10NF K 50V /0603 X7R
C339	291476R	CC-CHIP 470PF J 50V /0603 NP0 T&R	C458	293113R	CC-CHIP 10NF K 50V /0603 X7R
C340	291476R	CC-CHIP 470PF J 50V /0603 NP0 T&R	C459	293113R	CC-CHIP 10NF K 50V /0603 X7R
C335	291561R	CC-CHIP 560PF J 50V /0603 NPO TAPE	C460	293113R	CC-CHIP 10NF K 50V /0603 X7R
C336	291561R	CC-CHIP 560PF J 50V /0603 NPO TAPE	C461	293113R	CC-CHIP 10NF K 50V /0603 X7R
C363	291561R	CC-CHIP 560PF J 50V /0603 NPO TAPE	C462	293113R	CC-CHIP 10NF K 50V /0603 X7R
Q303	401142R	TRN-CHIP BC858BLT1G SOT23	L323	053804R	COIL-CHIP 10UH K 0805

POS	PART NUMBER	PART DESCRIPTION	POS	PART NUMBER	PART DESCRIPTION
Q311	401142R	TRN-CHIP BC858BLT1G SOT23	L324	053804R	COIL-CHIP 10UH K 0805
Q312	401142R	TRN-CHIP BC858BLT1G SOT23	C386	290475R	CC-CHIP 47PF J 50V /0603 NPO TAPE
Q313	401142R	TRN-CHIP BC858BLT1G SOT23	C387	290475R	CC-CHIP 47PF J 50V /0603 NPO TAPE
R329	172276R	RC-CHIP 2.7K J 1/16W /0603	D300	304412R	DIODE-CHIP ZENER BZX84C33 SOT23
U601	453124R	IC-CHIP NCP1117DT33RK G TO-252 PACKAGE	R233	172338R	RC-CHIP 3.3K J 1/10W /0603
U606	453124R	IC-CHIP NCP1117DT33RK G TO-252 PACKAGE	R234	172338R	RC-CHIP 3.3K J 1/10W /0603
U603	453295R	IC-CHIP NCP1117DT18RK G TO252 (T&R)	R337	172338R	RC-CHIP 3.3K J 1/10W /0603
U203	453355R	IC M25P40 - VMN6T	R338	172338R	RC-CHIP 3.3K J 1/10W /0603
R374	170154R	RC-CHIP 150R J 1/16W /0603 TAPE	R324	172338R	RC-CHIP 3.3K J 1/10W /0603
R375	170154R	RC-CHIP 150R J 1/16W /0603 TAPE	C638	293235R	CC-CHIP 22NF J 16V /0603 X7R
R330	170154R	RC-CHIP 150R J 1/16W /0603 TAPE	R326	170333R	RC-CHIP 33R J 1/16W /0603 TAPE
R331	170154R	RC-CHIP 150R J 1/16W /0603 TAPE	R327	170333R	RC-CHIP 33R J 1/16W /0603 TAPE
R332	170154R	RC-CHIP 150R J 1/16W /0603 TAPE	R328	170333R	RC-CHIP 33R J 1/16W /0603 TAPE
C417	291337R	CC-CHIP 330PF J 50V /0603 NPO	R412	171107R	RC-CHIP 100R J 1/16W /0603
C418	291337R	CC-CHIP 330PF J 50V /0603 NPO	R413	171107R	RC-CHIP 100R J 1/16W /0603
L309	053806R	COIL-CHIP 8.2UH K /0805	R403	173100R	RC-CHIP 10K J 1/10W /0603
L201	053725R	COIL-CHIP 10UH %20/0805	R420	173471R	RC-CHIP 47K J 1/10W /0603
L203	053725R	COIL-CHIP 10UH %20/0805	R421	173471R	RC-CHIP 47K J 1/10W /0603
L302	053725R	COIL-CHIP 10UH %20/0805	D400	303497R	DIODE CHIP IMBD4148 SOT 23
L303	053725R	COIL-CHIP 10UH %20/0805	D401	303818R	DIODE-CHIP BAV99LT1 SOT23 T&R
L304	053725R	COIL-CHIP 10UH %20/0805	D402	303818R	DIODE-CHIP BAV99LT1 SOT23 T&R
L305	053725R	COIL-CHIP 10UH %20/0805	D403	303818R	DIODE-CHIP BAV99LT1 SOT23 T&R
L306	053725R	COIL-CHIP 10UH %20/0805	D404	303818R	DIODE-CHIP BAV99LT1 SOT23 T&R
L307	053725R	COIL-CHIP 10UH %20/0805	D405	303818R	DIODE-CHIP BAV99LT1 SOT23 T&R
L308	053725R	COIL-CHIP 10UH %20/0805	U400	453010R	IC-CHIP M24C02 - MN6TP SO8
L310	053725R	COIL-CHIP 10UH %20/0805	C627	252476R	EC 470UF 25V 11*10 R:5
L311	053725R	COIL-CHIP 10UH %20/0805	C637	252476R	EC 470UF 25V 11*10 R:5
L316	053725R	COIL-CHIP 10UH %20/0805	C347	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
L400	053725R	COIL-CHIP 10UH %20/0805	C361	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
R351	171476R	RC-CHIP 470R J 1/16W /0603	C362	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
R353	171476R	RC-CHIP 470R J 1/16W /0603	C364	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
R354	171476R	RC-CHIP 470R J 1/16W /0603	C365	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
R414	171476R	RC-CHIP 470R J 1/16W /0603	C366	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
C256	294234R	CC-CHIP 220NF K 16V /0603 X7R	C367	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
C396	294234R	CC-CHIP 220NF K 16V /0603 X7R	C441	251478R	EC 47UF 16V 11*5 R:5
C397	294234R	CC-CHIP 220NF K 16V /0603 X7R	C442	251478R	EC 47UF 16V 11*5 R:5
C398	294234R	CC-CHIP 220NF K 16V /0603 X7R	C107	252476R	EC 470UF 25V 11*10 R:5
C399	294234R	CC-CHIP 220NF K 16V /0603 X7R	C112	252105R	EC 100UF 50V 12*8 R:5
L317	053804R	COIL-CHIP 10UH K 0805	C150	251222R	EC 22UF 50V RS 11*6.3 TAPING
L319	053804R	COIL-CHIP 10UH K 0805	C411	250332R	EC 3.3UF 50V 11*5 R:5
C350	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM	C443	251478R	EC 47UF 16V 11*5 R:5
C354	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM	C444	251478R	EC 47UF 16V 11*5 R:5
C355	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM	C384	251478R	EC 47UF 16V 11*5 R:5
C356	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM	C410	252105R	EC 100UF 50V 12*8 R:5
C357	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM	C368	252112R	EC 100UF 16V 11*6 R:5
C358	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM	C369	252112R	EC 100UF 16V 11*6 R:5
C360	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM	C370	252112R	EC 100UF 16V 11*6 R:5
C464	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM	C630	252112R	EC 100UF 16V 11*6 R:5
C346	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM	C631	252112R	EC 100UF 16V 11*6 R:5
C359	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM	C632	252112R	EC 100UF 16V 11*6 R:5
C409	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM	C633	252112R	EC 100UF 16V 11*6 R:5
C247	251222R	EC 22UF 50V RS 11*6.3 TAPING	C634	252112R	EC 100UF 16V 11*6 R:5
C248	251222R	EC 22UF 50V RS 11*6.3 TAPING	C635	252112R	EC 100UF 16V 11*6 R:5
C249	251222R	EC 22UF 50V RS 11*6.3 TAPING	C341	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
C250	251222R	EC 22UF 50V RS 11*6.3 TAPING	C342	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
C333	251222R	EC 22UF 50V RS 11*6.3 TAPING	C343	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
C334	251222R	EC 22UF 50V RS 11*6.3 TAPING	C344	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
C412	250479R	EC 4.7UF 50V 11*5 R:5	C345	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM

POS	PART NUMBER	PART DESCRIPTION	POS	PART NUMBER	PART DESCRIPTION
C403	294234R	CC-CHIP 220NF K 16V /0603 X7R	C348	251112R	EC 10UF 50V RS 11*5 TAPING R=5MM
C404	294234R	CC-CHIP 220NF K 16V /0603 X7R	C419	291337R	CC-CHIP 330PF J 50V /0603 NPO
C332	294125R	CC-CHIP 100NF K 25V /0603 X7R	C420	291337R	CC-CHIP 330PF J 50V /0603 NPO
C402	294125R	CC-CHIP 100NF K 25V /0603 X7R	C382	292114R	CC-CHIP 1NF K 50V /0603 X7R
C329	294125R	CC-CHIP 100NF K 25V /0603 X7R	C383	292114R	CC-CHIP 1NF K 50V /0603 X7R
R371	170754R	RC-CHIP 75R J 1/16W /0603	C388	292114R	CC-CHIP 1NF K 50V /0603 X7R
R372	170754R	RC-CHIP 75R J 1/16W /0603	C389	292114R	CC-CHIP 1NF K 50V /0603 X7R
R373	170754R	RC-CHIP 75R J 1/16W /0603	C322	294125R	CC-CHIP 100NF K 25V /0603 X7R
C421	292114R	CC-CHIP 1NF K 50V /0603 X7R	C324	294125R	CC-CHIP 100NF K 25V /0603 X7R
C422	292114R	CC-CHIP 1NF K 50V /0603 X7R	C326	294125R	CC-CHIP 100NF K 25V /0603 X7R
R301	173100R	RC-CHIP 10K J 1/10W /0603	C323	294125R	CC-CHIP 100NF K 25V /0603 X7R
R319	173100R	RC-CHIP 10K J 1/10W /0603	L318	053804R	COIL-CHIP 10UH K 0805
R387	173100R	RC-CHIP 10K J 1/10W /0603	L321	053804R	COIL-CHIP 10UH K 0805
C400	294234R	CC-CHIP 220NF K 16V /0603 X7R	R313	173471R	RC-CHIP 47K J 1/10W /0603
C401	294234R	CC-CHIP 220NF K 16V /0603 X7R	R314	173471R	RC-CHIP 47K J 1/10W /0603
Q301	401141R	TRN-CHIP BC848BLT1G SOT23	R315	173471R	RC-CHIP 47K J 1/10W /0603
Q308	401141R	TRN-CHIP BC848BLT1G SOT23	R316	173471R	RC-CHIP 47K J 1/10W /0603
Q304	401142R	TRN-CHIP BC858BLT1G SOT23	R317	173471R	RC-CHIP 47K J 1/10W /0603
Q305	401142R	TRN-CHIP BC858BLT1G SOT23	R318	173471R	RC-CHIP 47K J 1/10W /0603
Q306	401142R	TRN-CHIP BC858BLT1G SOT23	R320	173471R	RC-CHIP 47K J 1/10W /0603
R376	170154R	RC-CHIP 150R J 1/16W /0603 TAPE	R321	173471R	RC-CHIP 47K J 1/10W /0603
R377	170154R	RC-CHIP 150R J 1/16W /0603 TAPE	U302	452985R	IC-CHIP MC14053BDR2G SOIC16
R364	170754R	RC-CHIP 75R J 1/16W /0603	R335	172338R	RC-CHIP 3.3K J 1/10W /0603
R370	170754R	RC-CHIP 75R J 1/16W /0603	R336	172338R	RC-CHIP 3.3K J 1/10W /0603
R343	171107R	RC-CHIP 100R J 1/16W /0603	R333	172338R	RC-CHIP 3.3K J 1/10W /0603
R344	171107R	RC-CHIP 100R J 1/16W /0603	S125	032449R	KONN.MALE 2*15 30.LU SST
R399	171336R	RC-CHIP 330R J 1/16W /0603 TAPE	L116	053946R	COIL-CHIP B82464G4223M EPCOS
R400	171336R	RC-CHIP 330R J 1/16W /0603 TAPE	Q100	401141R	TRN-CHIP BC848BLT1G SOT23
R352	171476R	RC-CHIP 470R J 1/16W /0603	Q101	401141R	TRN-CHIP BC848BLT1G SOT23
R355	171476R	RC-CHIP 470R J 1/16W /0603	Q150	401141R	TRN-CHIP BC848BLT1G SOT23
R356	171476R	RC-CHIP 470R J 1/16W /0603	Q151	401141R	TRN-CHIP BC848BLT1G SOT23
R359	172104R	RC-CHIP 1K J 1/16W /0603	Q152	401141R	TRN-CHIP BC848BLT1G SOT23
R360	172104R	RC-CHIP 1K J 1/16W /0603	Q208	401141R	TRN-CHIP BC848BLT1G SOT23
R384	172479R	RC-CHIP 4.7K J 1/16W /0603 TAPE	R150	172479R	RC-CHIP 4.7K J 1/16W /0603 TAPE
R362	173183R	RC-CHIP 18K J 1/16W /0603 TAPE	R276	172479R	RC-CHIP 4.7K J 1/16W /0603 TAPE
R110	173229R	RC-CHIP 22K J 1/16W /0603	R277	172479R	RC-CHIP 4.7K J 1/16W /0603 TAPE
R152	170112R	RC-CHIP 2K J 1/16W /0603 TAPE	D100	303867R	DIODE-CHIP SL23 DO214AA
R106	171184R	RC-CHIP 180R J 1/16W /0603	R103	171107R	RC-CHIP 100R J 1/16W /0603
R153	171476R	RC-CHIP 470R J 1/16W /0603	R100	173100R	RC-CHIP 10K J 1/10W /0603
J100	179835R	RC-CHIP 0.75R %1 0805	R107	173100R	RC-CHIP 10K J 1/10W /0603
C113	291688R	CC-CHIP 680PF J 0603 50V NPO	R108	173100R	RC-CHIP 10K J 1/10W /0603
C101	293235R	CC-CHIP 22NF J 16V /0603 X7R	R151	173100R	RC-CHIP 10K J 1/10W /0603
U101	452667R	IC-CHIP MC34063ADR2G SO8 T&R	R155	173100R	RC-CHIP 10K J 1/10W /0603
U100	453553R	IC-CHIP MP1593DN-LF-Z DC-DC CONV SOIC8N	R156	173100R	RC-CHIP 10K J 1/10W /0603
D101	304413R	DIODE-CHIP PMEG4010EH SOD123	R104	173563R	RC-CHIP 56K J 1/16W /0603
C100	294125R	CC-CHIP 100NF K 25V /0603 X7R	J200	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE
C102	294125R	CC-CHIP 100NF K 25V /0603 X7R	J201	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE
C106	294125R	CC-CHIP 100NF K 25V /0603 X7R	J202	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE
C151	294125R	CC-CHIP 100NF K 25V /0603 X7R	J203	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE
C103	294125R	CC-CHIP 100NF K 25V /0603 X7R	J204	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE
C109	294125R	CC-CHIP 100NF K 25V /0603 X7R	J205	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE
C115	294125R	CC-CHIP 100NF K 25V /0603 X7R	J206	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE
J316	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE	J207	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE
R102	173183R	RC-CHIP 18K J 1/16W /0603 TAPE	J208	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE
R101	173563R	RC-CHIP 56K J 1/16W /0603	J209	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE
C104	293113R	CC-CHIP 10NF K 50V /0603 X7R	J318	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE
C636	292153R	CC-CHIP 1.5NF K 50V /0603 X7R TAPE	R154	172104R	RC-CHIP 1K J 1/16W /0603
R615	173563R	RC-CHIP 56K J 1/16W /0603	R157	172104R	RC-CHIP 1K J 1/16W /0603

POS	PART NUMBER	PART DESCRIPTION	POS	PART NUMBER	PART DESCRIPTION
D608	303867R	DIODE-CHIP SL23 DO214AA	R105	172224R	RC-CHIP 2.2K J 1/16W/0603 TAPE
L609	053946R	COIL-CHIP B82464G4223M EPCOS	R109	173229R	RC-CHIP 22K J 1/16W /0603
U600	453553R	IC-CHIP MP1593DN-LF-Z DC-DC CONV SOIC8N		X52527R	CABLE WITH.TERM.L=110MM YEL
C600	294125R	CC-CHIP 100NF K 25V /0603 X7R		ZF7524R	CABLE HARNESS AC POW PLUG-SW
C601	294125R	CC-CHIP 100NF K 25V /0603 X7R		L7J172	CU ASSY 32W L97. L5A (TX8193-10)
C602	294125R	CC-CHIP 100NF K 25V /0603 X7R	CN1	038889R	CONN.MALE 5 RIGHT-A 2317-5R
C603	294125R	CC-CHIP 100NF K 25V /0603 X7R	IR1	452521R-1	IR RECEIVER TSOP34838 SS1A
C604	294125R	CC-CHIP 100NF K 25V /0603 X7R	D1	303884R	LED 3MM WHITE 3V 5MA P.LIGHT
C625	293113R	CC-CHIP 10NF K 50V /0603 X7R	R2	101163R	CFR 150R J 1/4W 26MM
R601	173183R	RC-CHIP 18K J 1/16W /0603 TAPE	R1	101163R	CFR 150R J 1/4W 26MM
J307	031795R	CONN.S-VHS	R4	102141R	CFR 1K J 1/4W /6 26MM
J308	031163R	KONN. CINCH WHITE HOR.14.1	R8	101494R	CFR 470R J 1/4W /6 26MM
J311	031164R	KONN. CINCH RED HOR.14.1		L8J172	CU ASSY 32L97 L5A VER
J312	031165R	KONN. CINCH YELLOW HOR.14.1	CN1	032997R	CONN.HOUS.2 PIN 2317-2R
S303	031251R	SCART SOCKET 14.1		TX9174	CU ASSY PN 32L94 L5A VER.
C110	253128R	EC 1000UF 16V 20*10 R:5 LOW ESR	R3	101343R	CFR 330R J 1/4W /6 26MM
S100	031658R	CONN.HOUSING.10P 2MMM 89400-1010 MOLEX	R7	101494R	CFR 470R J 1/4W /6 26MM
S149	031658R	CONN.HOUSING.10P 2MMM 89400-1010 MOLEX	R5	101189R	CFR 180R J 1/4W /6 26MM
C111	252112R	EC 100UF 16V 11*6 R:5	R6	102141R	CFR 1K J 1/4W /6 26MM
C563	253227R	EC 2200UF 35V 16*25 R:7.5	R9	102400R	CFR 3.9K J 1/4W /6 26MM
C116	253115R	EC 1000UF 16V 20*10 R:5	SOURCE	010860R	TACT SW LONG STEN
S150	031476R	CONN.HOUSING.12P 2MM 89400-1210 MOLEX	VOL+	010860R	TACT SW LONG STEN
L103	053937R	BOBIN RAD. 100UH K R:5MM LHL06TB	VOL-	010860R	TACT SW LONG STEN
C105	253131R	EC 1000UF 35V 20*13 R:5	PROG+	010860R	TACT SW LONG STEN
JP203	031281R	CON.MALE 7.LI 2317-7S JST B 7B-XH-A WHIT	PROG-	010860R	TACT SW LONG STEN
TU351	QW1136RTH1	TUNER HOR. THOMSON CTF5547	MENU	010860R	TACT SW LONG STEN
C114	253115R	EC 1000UF 16V 20*10 R:5	CN2	031396R	CON.CINCH SST 396G1-R 3?LU
JP100	032951R	CONN.HOUSING.7.LI MOLEX 89400-0710	CN3	031396R	CON.CINCH SST 396G1-R 3?LU
JP101	032951R	CONN.HOUSING.7.LI MOLEX 89400-0710	SW1	010861R	ON/OFF SWITCH BK98
	KW5502R	CABLE PANEL LVDS 32# AUO-VERS.V5 L=300MM		TW5140	LC 26"/32" AUDIO AMPLIFIER
J451	BW9524R	CABLE HARNESS DC POWER 10 PIN L5 SAMSUN	C259	250115R	EC 1UF 50V 11*5 R:5
J450	KW3506R	CON.CAB. AUDIO MODULE/L5 CHASSIS L=200	C411	250115R	EC 1UF 50V 11*5 R:5
S421	KW3524R	CABLE HARNESS 7.LI AMP. 26"-32" L5A	C460	250227R	EC 2.2UF 16V 11*5 R:5
	MW1504R	CON.CAB. PSU/AUDIO MODULE L=380 MAKARON	C484	250227R	EC 2.2UF 16V 11*5 R:5
	031491R	PLUG AC INLET TWO PHASE NOISE FILTER	C250	294476R	CC-CHIP 470NF K 16V /0805 X7R
R448	173228R	RC-CHIP 22K J 1/10W /0603	C251	294476R	CC-CHIP 470NF K 16V /0805 X7R
R465	170102R	RC-CHIP 10R J 1/8W /1206	C496	294476R	CC-CHIP 470NF K 16V /0805 X7R
R466	170102R	RC-CHIP 10R J 1/8W /1206	C258	294122R	CC-CHIP 100NF K 50V /0603 X7R
R467	172824R	RC-CHIP 8.2K J 1/16W /0603 TAPE	C473	294122R	CC-CHIP 100NF K 50V /0603 X7R
U402	453494R	IC-CHIP TRIPATH TA2024 STEREO CLAS-D T&R	C493	294122R	CC-CHIP 100NF K 50V /0603 X7R
R468	179005R	RC-CHIP 0R /0603 1.6*0.8 TAPE	C254	292114R	CC-CHIP 1NF K 50V /0603 X7R
C471	252241R	EC 220UF 35V WL 16*8 LESR/HRPL	C255	292114R	CC-CHIP 1NF K 50V /0603 X7R
C472	252241R	EC 220UF 35V WL 16*8 LESR/HRPL	C256	292114R	CC-CHIP 1NF K 50V /0603 X7R
S409	031194R	CONN.HOUS.4P 2317-4S JST B 4B-XH-A WHITE	C257	292114R	CC-CHIP 1NF K 50V /0603 X7R
S421	032951R	CONN.HOUSING.7.LI MOLEX 89400-0710	C495	292114R	CC-CHIP 1NF K 50V /0603 X7R
CAB1	KW3527R	CAB.TERM. L5/AUDIO MODULE GROUND L=280	C422	294234R	CC-CHIP 220NF K 16V /0603 X7R
S422	031387R	CON.MALE 8POL.250G1-V08	D407	303867R	DIODE-CHIP SL23 DO214AA
S423	031387R	CON.MALE 8POL.250G1-V08	D408	303867R	DIODE-CHIP SL23 DO214AA
L412	051371R	LINE FILTER 2X28MH 3A	D409	303867R	DIODE-CHIP SL23 DO214AA
	Y56913R	ADAPTOR AC12V/4A 15"CLASSII W/O GND	D410	303867R	DIODE-CHIP SL23 DO214AA
TU301	Y11137R	TUNER HOR. SAMSUNG TECC2949PG39E	L405	055622R	FERRIT BEAD-CHIP 100MHZ 4A
	C4A187F	U/K L5A KUMANDA KMK-01 SILVER BEKO S.LI	L406	055622R	FERRIT BEAD-CHIP 100MHZ 4A
	Y92913R	ADAPTOR AC12V/5A CLASS II W/O GND UK TYPE	L411	055622R	FERRIT BEAD-CHIP 100MHZ 4A
	038948R	MAIN CABLE CLSII UK TYPE	R434	173228R	RC-CHIP 22K J 1/10W /0603
	8R9183RFJ1	INVERTOR 17"W FUJITSU PLCD0817410	R435	173228R	RC-CHIP 22K J 1/10W /0603
S503	Y56502R	KAB.PANEL INTERFACE LCD TV 15 MOLEX L	R437	173228R	RC-CHIP 22K J 1/10W /0603
	X60183RSS2	INVERTOR 15 LTM150XH-L06A (PLCD2615412)	F600	054290R	FUSE 5A/250V ROUND
	ZH1183RLP2	INVERTOR 20" LC201V02-A3KB (PLCD0320613)			

FREQUENCY TABLE (MHz)

Channel	Number	BG	I	DK	L/L'
CH	1		49.75	49.75	47.75
CH	2	48.25	59.25	59.25	55.75
CH	3	55.25	77.25	77.25	60.50
CH	4	62.25	85.25	85.25	63.75
CH	5	175.25	93.25	93.25	176.00
CH	6	182.25	175.25	175.25	184.00
CH	7	189.25	183.25	183.25	192.00
CH	8	196.25	191.25	191.25	200.00
CH	9	203.25	199.25	199.25	208.00
CH	10	210.25	207.25	207.25	216.00
CH	11	217.25	215.25	215.25	189.25
CH	12	224.25	223.25	223.25	182.25
CH	13	53.75	45.75		196.25
CH	14	62.25	53.75		210.25
CH	15	82.25	61.75		
CH	16	175.25	69.75		
CH	17	183.25	95.25		
CH	18	192.25			
CH	19	201.25			
CH	20	210.25			
CH	21	471.25	471.25	471.25	471.25
CH	22	479.25	479.25	479.25	479.25
CH	23	487.25	487.25	487.25	487.25
CH	24	495.25	495.25	495.25	495.25
CH	25	503.25	503.25	503.25	503.25
CH	26	511.25	511.25	511.25	511.25
CH	27	519.25	519.25	519.25	519.25
CH	28	527.25	527.25	527.25	527.25
CH	29	535.25	535.25	535.25	535.25
CH	30	543.25	543.25	543.25	543.25
CH	31	551.25	551.25	551.25	551.25
CH	32	559.25	559.25	559.25	559.25
CH	33	567.25	567.25	567.25	567.25
CH	34	575.25	575.25	575.25	575.25
CH	35	583.25	583.25	583.25	583.25
CH	36	591.25	591.25	591.25	591.25
CH	37	599.25	599.25	599.25	599.25
CH	38	607.25	607.25	607.25	607.25
CH	39	615.25	615.25	615.25	615.25
CH	40	623.25	623.25	623.25	623.25
CH	41	631.25	631.25	631.25	631.25
CH	42	639.25	639.25	639.25	639.25
CH	43	647.25	647.25	647.25	647.25
CH	44	655.25	655.25	655.25	655.25

Channel	Number	BG	I	DK	L/L'
CH	45	663.25	663.25	663.25	663.25
CH	46	671.25	671.25	671.25	671.25
CH	47	679.25	679.25	679.25	679.25
CH	48	687.25	687.25	687.25	687.25
CH	49	695.25	695.25	695.25	695.25
CH	50	703.25	703.25	703.25	703.25
CH	51	711.25	711.25	711.25	711.25
CH	52	719.25	719.25	719.25	719.25
CH	53	727.25	727.25	727.25	727.25
CH	54	735.25	735.25	735.25	735.25
CH	55	743.25	743.25	743.25	743.25
CH	56	751.25	751.25	751.25	751.25
CH	57	759.25	759.25	759.25	759.25
CH	58	767.25	767.25	767.25	767.25
CH	59	775.25	775.25	775.25	775.25
CH	60	783.25	783.25	783.25	783.25
CH	61	791.25	791.25	791.25	791.25
CH	62	799.25	799.25	799.25	799.25
CH	63	807.25	807.25	807.25	807.25
CH	64	815.25	815.25	815.25	815.25
CH	65	823.25	823.25	823.25	823.25
CH	66	831.25	831.25	831.25	831.25
CH	67	839.25	839.25	839.25	839.25
CH	68	847.25	847.25	847.25	847.25
CH	69	855.25	855.25	855.25	855.25
CH	70		863,25		863.25
CH	71		871,25		
CH	72		879,25		
CH	73		887,25		160.00
CH	74	69.25			172.00
CH	75	76.25			220.00
CH	76	83.25			232.00
CH	77	90.25			244.00
CH	78	97.25			256.00
CH	79	59.25			268.00
CH	80	93.25			280.00
S	1	105.25	103.25	103.25	116.75
S	2	112.25	111.25	111.25	128.75
S	3	119.25	119.25	119.25	140.75
S	4	126.25	127.25	127.25	152.75
S	5	133.25	135.25	135.25	164.75
S	6	140.25	143.25	143.25	176.75
S	7	147.25	151.25	151.25	188.75
S	8	154.25	159.25	159.25	200.75
S	9	161.25	167.25	167.25	212.75
S	10	168.25	231.25	231.25	224.75
S	11	231.25	239.25	239.25	236.75
S	12	238.25	247.25	247.25	248.75
S	13	245.25	255.25	255.25	260.75
S	14	252.25	263.25	263.25	272.75

Channel	Number	BG	I	DK	L/L'
S	15	259.25	271.25	271.25	284.75
S	16	266.25	279.25	279.25	296.75
S	17	273.25	287.25	287.25	55.75
S	18	280.25	295.25	295.25	60.50
S	19	287.25	303.25	303.25	63.75
S	20	294.25			
S	21	303.25			303.25
S	22	311.25	311.25	311.25	311.25
S	23	319.25	319.25	319.25	319.25
S	24	327.25	327.25	327.25	327.25
S	25	335.25	335.25	335.25	335.25
S	26	343.25	343.25	343.25	343.25
S	27	351.25	351.25	351.25	351.25
S	28	359.25	359.25	359.25	359.25
S	29	367.25	367.25	367.25	367.25
S	30	375.25	375.25	375.25	375.25
S	31	383.25	383.25	383.25	383.25
S	32	391.25	391.25	391.25	391.25
S	33	399.25	399.25	399.25	399.25
S	34	407.25	407.25	407.25	407.25
S	35	415.25	415.25	415.25	415.25
S	36	423.25	423.25	423.25	423.25
S	37	431.25	431.25	431.25	431.25
S	38	439.25	439.25	439.25	439.25
S	39	447.25	447.25	447.25	447.25
S	40	455.25	455.25	455.25	455.25
S	41	463.25	463.25	463.25	463.25

M6Y000: TV TOSH/HAV 20LCL25 BS/CG P/NX/2/K/SV/VG/20VL55G

Position	Part Code	Description	Date
AYKTABAN	011815R	SCREW SELF TAPP. 2.9*9.5 W/W	15.12.2005 04:17:59
C253	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
C330	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
C331	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
C457	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
C458	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
C459	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
C460	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
C461	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
C462	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
C463	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
C508	252105R	EC 100UF 50V 12*8 R:5	17.12.2005 04:05:39
C523	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
C625	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005

			04:06:00
C626	293113R	CC-CHIP 10NF K 50V /0603 X7R	09.12.2005 04:06:00
HOP	011815R	SCREW SELF TAPP. 2.9*9.5 W/W	15.12.2005 04:18:01
HOP-KLK-KAB	055127R-1	CORE FERRIT	20.12.2005 04:06:50
IR1	452521R-1	IR RECEIVER TSOP34838 SS1A	20.12.2005 04:06:50
MERCEK	011814R	SCREW SELF TAPPING 2.9*9.5	15.12.2005 04:18:01
PLS	044861	PE BAG 260*90*.05	20.12.2005 04:06:50
R235	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R236	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R239	172104R	RC-CHIP 1K J 1/16W /0603	09.12.2005 04:06:00
R240	172104R	RC-CHIP 1K J 1/16W /0603	09.12.2005 04:06:00
R241	172104R	RC-CHIP 1K J 1/16W /0603	09.12.2005 04:06:00
R255	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R257	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R258	172104R	RC-CHIP 1K J 1/16W /0603	09.12.2005 04:06:00

R341	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R342	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R345	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R346	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R347	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R348	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R357	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R358	172104R	RC-CHIP 1K J 1/16W /0603	09.12.2005 04:06:00
R418	172104R	RC-CHIP 1K J 1/16W /0603	09.12.2005 04:06:00
R419	172104R	RC-CHIP 1K J 1/16W /0603	09.12.2005 04:06:00
R423	172104R	RC-CHIP 1K J 1/16W /0603	09.12.2005 04:06:00
R424	172104R	RC-CHIP 1K J 1/16W /0603	09.12.2005 04:06:00
R501	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R502	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R503	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00

R504	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R605	171107R	RC-CHIP 100R J 1/16W /0603	09.12.2005 04:06:00
R607	172104R	RC-CHIP 1K J 1/16W /0603	09.12.2005 04:06:00
SEFFAPARCA	011814R	SCREW SELF TAPPING 2.9*9.5	15.12.2005 04:17:59
S301	031251R	SCART SOCKET 14.1	20.12.2005 04:06:50
S303	031251R	SCART SOCKET 14.1	20.12.2005 04:06:50
S600	031675R	CON.HOUSING 2P MALE	20.12.2005 04:06:50
TUSTK	011814R	SCREW SELF TAPPING 2.9*9.5	15.12.2005 04:18:00
	LN4825	WARANTY CARD TOSHIBA GER+FRA	
	Y48913R	ADAPTOR AC 15V 4.6A 20" CLASS II	
	ZC5850-00A	ACCESSORIE BOX 20" LCD TV BEKO	
	ZF9187F	RC L5A TOSHIBA GRI/SHINE SLP.ED CT-873	
	ZG4116	TOSHIBA METAL FOOT LCD TV 20" BRI.SIL	
	ZG4251F	"FRONT COVER TOSHIBA BRI.SIL.B.LI 20"" L	
	044518-01	PE BAG 650*600*0.5 B.LI	
	044783-03	PE BAG 230*430*.06 PRESSED HOLE	

	045152-01	LABEL BAR CODE 90*40	
	045411-01	LABEL 90*56	
	045417	LABEL 20*45 CHASSIS	
	056L20-AU10	LCD AU A201SN02 V4 (20"LCD TV)-CHINA	
	090118-01	SOLDER BAR (L-SN 60PB)1.2MM	
	500276	HOLDER MAIN POWER (FASON)	
	500297	CABLE HOLDER 5P	
	885906R	BATTERY AAA 1.5V	