

Parts List

No.	Parent	Lvl	Loc.	Material Code	Description & Specification	SNA
1	AK96-01892A	3	MF01A	AK94-00540A	ASSY PCB FRONT; BD-E8900,ASSY PCB FRONT	SA
10	AK96-01894A	3	EF01	3103-001290	FAN-DC; 12 VDC,2200rpm,0.147m ³ /mi,0.921m	SA
11	AK91-01136B	2	P025	3903-000176	CBF-POWER CORD; AT,EU,CP2,HOUSING(2P),250	SA
12	AK90-00152J	2		AK96-01579J	ASSY DECK P; BD-E8900,MOLD,H/H SLOT IN DE	SA
13	AK91-01136B	2	M0081	6003-001375	SCREW-TAPTYPE; BH,+,-,B,M3,L8,ZPC(WHT),SW	SA
14	AK91-01136B	2	W391	6003-000275	SCREW-TAPTYPE; BH,+,-,B,M3,L10,ZPC(BLK),SWR	SA
2	AK91-01151A	2	M0014	AK94-00571A	ASSY PCB MAIN; BD-E8300/ZF,MAIN PCB ASSY	SA
3	AK91-01151A	2	P001A	AK94-00513A	ASSY PCB SMPS; BD-E8500,XF,SMPS ASSY,1L	SA
4	AK91-01151A	2		AK59-00138A	NETWORK-WLAN MODULE; DNUB-S234B,BCM43234B	SA
5	AK96-01892A	3	MF01A	AK94-00540A	ASSY PCB FRONT; BD-E8900,ASSY PCB FRONT	SA
6	AK96-01892A	3		AK94-00541A	ASSY PCB S-USB; BD-E8900,ASSY SUB-USB	SA
7	AK96-01892A	3	FD12	AK64-02544A	DOOR-USB; BD-D5300,ABS,T2.0,H40,W50,L20,B	SA
8	AK90-00235A	2	F001A	AK96-01892A	ASSY COVER P-FRONT; BD-E8500,PMMA+ABS	SA
9	AK91-01136B	2	T001A	AK96-01893A	ASSY COVER P-TOP; BD-E8500,PMMA+ABS	SA

2. Electrical Parts List

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
			BD-E8300/ZF (QH02)		
1	D001A	AK90-00152J	ASSY DECK;BD-ES6000,MOLD BASE,8th PICK-U	1	SNA
..2		AK96-01579J	ASSY DECK P;BD-E8900,MOLD,H/H SLOT IN DE	1	SA
..3	W012	6002-001086	SCREW-TAPPING;PH,+,B,M1.7,L5.0,ZPC(WHT),	1	SA
..3	SCREW	6003-001795	SCREW-TAPTYPE;PWH,B,M2,L6,ZPC(WHT),SWCH1	4	SNA
..3		AK96-01552A	ASSY MISC P-HINGE-PU;BD-P7,BUCH	1	SNA
...4	DH03	AK61-01097A	HINGE-PU;BD-P7,POM	1	SNA
...4	ES09	AK61-01148A	SPRING ETC-HINGE PU;BD-P7,STAINLESS-STS3	1	SNA
..3		AK96-01581G	ASSY DECK P-EMPTY;BD-E8900,MOLD,SLOT IN	1	SNA
...4	S.N.A	0205-001033	GREASE;PL-30G,W050030019	0	SNA
...4	FL06	3809-002718	FFC CABLE-FLAT;60V,105160mm,15P,1.0m	1	SNA
...4	FL06	3809-002722	FFC CABLE-FLAT;60V,105215mm,40P,0.5m	1	SNA
...4		AK63-00900A	SHEET-FELT;BD-E6500, BD-ES6000,FELT,0.45	1	SNA
...4		AK96-01507A	ASSY FRAME P-MAIN;BD-D6500/D6700/D6900	1	SNA
....5	W274	6001-001730	SCREW-MACHINE;BH,+,M1.7,L2.5,ZPC(WHT),SW	2	SA
....5	W396	6003-001620	SCREW-TAPTYPE;CH,+,B,M1.4,L5,NI PLT,SWRC	1	SNA
....5		AK31-00054B	MOTOR DC-LOAD;SCRF-300CA-16L,2670,3.9V,1	1	SNA
....5		AK61-01085A	BODY-LIFT-CHUCK;BD-D6500,D6700,D6900,POM	2	SNA
....5	SNA	AK61-01086A	BASE-MAIN;BD-D6500,D6700,D6900,ABS+GF,1.	1	SNA
....5		AK61-01165A	SPRING ETC-TOGGLE;BD-D6500,D6700,D6900,S	1	SNA
....5		AK61-01166A	SPRING ETC-PLATE-CHUCK;BD-D6500,D6700,D6	1	SNA
....5	DS02	AK66-00194A	SLIDER-CAM;BD-D6500,D6700,D6900,ABS+GF20	1	SNA
....5		AK66-00195A	LINK-LIFT-CHUCK;BD-D6500,D6700,D6900,ABS	2	SNA
....5		AK66-00196A	GEAR-RELAY2;BD-D6500,D6700,D6900,POM,0.4	3	SNA
....5		AK66-00197A	GEAR-SLIDER;BD-D6500,D6700,D6900,POM,0.4	1	SNA
....5		AK66-00198A	GEAR-RELAY1;BD-D6500,D6700,D6900,TPE,0.4	1	SNA
....5	DG06	AK66-00199A	GEAR-PULLEY;BD-D6500,D6700,D6900,POM,0.4	1	SNA
....5	SNA	AK66-00200A	PULLEY-MOTOR;BD-D6500,D6700,D6900,POM,WH	1	SNA
....5	AP090	AK66-00227A	PULLEY-BELT;BD-D6500/D6700/D6900,EPDM,BL	1	SNA
....5		AK96-01508A	ASSY HOLDER P-ROLLER;BD-D6500/D6700/D690	1	SNA
....6		AK61-01084A	HOLDER-ROLLER;BD-D6500,D6700,6900,ABS+GF	1	SNA
....6		AK61-01163A	SPRING ETC-ROLLER;BD-D6500,D6700,D6900,S	2	SNA
....6		AK61-01196A	ROLLER-WASHER;BD-D6500,D6700,D6900,POLYS	2	SNA
....6		AK66-00193A	GEAR-ROLLER;BD-D6500,D6700,D6900,POM,0.4	1	SNA
....6		AK66-00225A	SHAFT-ROLLER;BD-D6500,D6700,D6900,STAINL	1	SNA
....6		AK66-00226A	ROLLER-LOAD;BD-D6500,D6700,D6900,SILICON	2	SNA
....5		AK96-01510A	ASSY MISC P-PLATE CHUCK;BD-D6500/D6700/D	1	SNA
....6		AK61-01083A	BODY-CLAMPER-DISC;BD-D6500,D6700,6900,PO	1	SNA

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
.....6	AP060	AK61-01087A	PLATE-CHUCK;BD-D6500,D6700,D6900,SUS304-	1	SNA
.....6		AK61-01088A	HOLDER-CLAMP;BD-D6500,D6700,D6900,SUS301	1	SNA
.....6		AK62-00040A	YOKE-CLAMP;BD-D6500,D6700,D6900,SPTE,0.3	1	SNA
....4	T001A	AK96-01509A	ASSY COVER P-TOP;BD-D6500/D6700/D6900	1	SNA
....5	SCREW	6003-001647	SCREW-TAPTYPE;FH,M1.7,+,L4,B,ZPC(BLK),P0	5	SNA
....5	SCW25	6003-001742	SCREW-TAPTYPE;CH,+,B,M2,L5,ZPC(WHT),SWRC	4	SA
....5		AK61-01080A	GUIDE-DISC-L;BD-D6500,D6700,6900,POM,55.	1	SNA
....5		AK61-01081A	GUIDE-DISC-R;BD-D6500,D6700,6900,POM,55.	1	SNA
....5		AK61-01082A	BASE-COVER;BD-D6500,D6700,6900,ABS+GF,1.	1	SNA
....5		AK61-01164A	SPRING ETC-GUIDE;BD-D6500,D6700,D6900,ST	2	SNA
....5	T001	AK63-00728A	COVER-TOP;BD-D6500,D6700,D6900,Others,0.	1	SNA
....5		AK63-00746A	SHEET-COVER;BD-D6500,D6700,D6900,Others,	1	SNA
....5		AK66-00185A	ARM-GUIDE-FL;BD-D6500,D6700,6900,POM,1mm	1	SNA
....5		AK66-00186A	ARM-GUIDE-FR;BD-D6500,D6700,6900,POM,1mm	1	SNA
....5		AK66-00187A	LINK-GUIDE-FRONT;BD-D6500,D6700,6900,ABS	1	SNA
....5		AK66-00188A	ARM-GUIDE-RL;BD-D6500,D6700,6900,POM,1mm	1	SNA
....5		AK66-00189A	ARM-GUIDE-RR;BD-D6500,D6700,6900,POM,1mm	1	SNA
....5		AK66-00190A	LINK-GUIDE-REAR;BD-D6500,D6700,D6900,ABS	1	SNA
....5		AK66-00191A	LINK-SELECT;BD-D6500,D6700,D6900,POM,1.1	1	SNA
....5		AK66-00192A	LEVER-SLIDER;BD-D6500,D6700,D6900,ABS+GF	1	SNA
....5	AL006	AK68-00433D	LABEL-CAUTION;BD-D6500,D6700,D6900,PAPER	1	SNA
....5		AK96-01506A	ASSY PCB P-DECK;BD-D6500/D6700/D6900	1	SNA
.....6	CD520	3409-001741	SWITCH-DETECTOR;3-5V,0.05~10mA,1C1P,51gf	3	SNA
.....6	CN3	3708-001878	CONNECTOR-FPC/FFC/PIC;6P,1mm,SMD-A,SnPb,	1	SA
.....6		AK41-01016A	PCB-DECK;BD-D4500/D4700/D4900,PHENOL,1,0	1	SNA
....4		AK96-01545A	ASSY MISC P-TRAVERS;BD-P7	1	SNA
....5	W011	6001-001370	SCREW-MACHINE;CH,+,M1.7,L3.0,ZPC(YEL),SW	3	SA
....5		6001-002658	SCREW-MACHINE;PH,M2.6,L5,ZPC(BLK),SWRCH1	4	SNA
....5	M0081	6003-001070	SCREW-TAPTYPE;BH,+,B,M2,L4,ZPC(BLK),SWRC	3	SNA
....5	H203	AH61-50327A	SHAFT-PU L84.7;BD-P,SUS420J2,L84.7,OD3,W	1	SNA
....5	SNA	AK31-00053A	MOTOR STEP-FEED;BD-P7	1	SNA
....5		AK31-00055A	MOTOR BLDC-SPINDLE;3600,12,250,BD-P7,130	1	SNA
....5	DB04	AK61-01093A	BRACKET-SHAFT PU;BD-P7,STAINLESS-ST304,	3	SNA
....5	SNA	AK61-01094A	BRACKET-SHAFT FIX;BD-P7,STAINLESS-ST304	1	SNA
....5	SNA	AK61-01095A	BRACKET-DECK;BD-P7,EGI-SECC,T1.6,W120,L1	1	SNA
....5	S.N.A	AK66-00050A	SHAFT-PU L98;BD-P,SUS420J2,L98,OD3,NTR,M	1	SNA
....5		AK73-00092A	RUBBER-DAMPER;BD-P7,BUTYL	4	SNA
...3		AK96-01838A	ASSY PICK UP P;SOH-BP8	1	SNA
....4	S.N.A	0201-000169	ADHESIVE-CYA;ARCN-A501F,NTR	0	SNA
....4	S.N.A	0201-001081	ADHESIVE-AA;1401C,RED,-,BOND-LOCK SCREW	0	SNA

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
...4	S.N.A	0201-001525	ADHESIVE-UV;8840L,YEL,TRANS,23000,DISCMA	0	SNA
...4	S.N.A	0201-001819	ADHESIVE-UV;8833M,YELLOW,21000mPas,89%(H	0	SNA
...4		0201-002088	ADHESIVE-UV;IM127S,YEL,13000mPa.s,1mmt,	0	SNA
...4		0202-001618	SOLDER-WIRE FLUX;LFA3-107,D0.5,96.5Sn/3.	0	SNA
...4		AK63-00874A	COVER-ACT;SOH-BP8,STAINLESS-ST304,0.2T,	1	SNA
...4		AK67-00050A	LENS-OL DVD CD;SOH-BP1,PLASTIC,NTR,PI3.8	1	SNA
...4		AK67-00099A	LENS-BD OL;VS3504/VDP10V4,Plastic,NTR,Pi	1	SNA
...4		AK68-01760A	LABEL-STICKER;SOH-BP5,0.1,10,15,WHITE	1	SNA
...4		AK96-01826A	ASSY PICK UP P-ACT;SOH-BP8	1	SNA
....5	S.N.A	0201-001081	ADHESIVE-AA;1401C,RED,-,BOND-LOCK SCREW	0	SNA
....5	S.N.A	0201-001230	ADHESIVE-CYA;LOCTITE 480,BLK,300,-	0	SNA
....5	S.N.A	0201-001537	ADHESIVE-UV;SDM-378,WHT,11000mPas,-	0	SNA
....5	S.N.A	0201-001793	ADHESIVE-UV;8791L3,WHITE,20000mPa.s	0	SNA
....5		3302-001884	MAGNET-RARE EARTH;48MGOe,9x6.1x1.4mm	2	SNA
....5	S.N.A	3812-001419	WIRE-NO SHEATH CU;SCW,0V,18.5mm,1/0.11mm	4	SNA
....5	WA001	3812-001456	WIRE-NO SHEATH CU;SCM,18.5,YELLOW	2	SNA
....5	W377	6001-001291	SCREW-MACHINE;CH,+,M1.7,L4,ZPC(BLK),SWRC	2	SA
....5	M0114	AK61-00969A	HOLDER-WIRE;SOH-BP6,PPS,13.8,8.65,BLACK	1	SNA
....5	SNA	AK62-00050A	YOKE-ACT;SOH-BP8,SPCC,1.2t,16.8,29.0,whi	1	SNA
....5		AK96-01184A	ASSY PICK UP P-BLADE;SOH-BP6	1	SNA
....6	SNA	AK66-00163A	BLADE-ACT;SOH-BP6,E5006L,BEIGE	1	SNA
...4		AK96-01842A	ASSY PICK UP P-OPT;SOH-BP8	1	SNA
....5	S.N.A	0201-001525	ADHESIVE-UV;8840L,YEL,TRANS,23000,DISCMA	0	SNA
....5	S.N.A	0201-001819	ADHESIVE-UV;8833M,YELLOW,21000mPas,89%(H	0	SNA
....5		0201-002088	ADHESIVE-UV;IM127S,YEL,13000mPa.s,1mmt,	0	SNA
....5		0202-001618	SOLDER-WIRE FLUX;LFA3-107,D0.5,96.5Sn/3.	0	SNA
....5		0205-001226	GREASE;FLOIL KG-513,WHT,1KG	0	SNA
....5		0602-001182	DIODE-LASER;6mW,2V,655nm,TP	1	SNA
....5		0602-001197	DIODE-LASER;25mW,2V,405nm,TP	1	SNA
....5	W376	6001-000805	SCREW-MACHINE;CH,+,-,M1.7,L3,NI PLT,SWRC	3	SNA
....5	W291	6001-001155	SCREW-MACHINE;PH(PI2.5),+,M1.4,L3.5,ZPC(	1	SNA
....5		AK31-00048A	MOTOR STEP-CLD;SOH-BP7,3V,25~35,3V,-10 ~	1	SNA
....5		AK61-00742A	SPRING ETC-DVD GT;SOH-DR4,Cu,2.8,5.6,5.6	1	SNA
....5		AK61-00830A	HOLDER-GT BD;SOH-BP4,Zn,T1.85,D5.6,GRY	1	SNA
....5		AK61-00874A	SPRING ETC-PBS BD;SOH-BP5,SUS,0.15,SILBE	1	SNA
....5	ES02	AK61-00974A	SPRING ETC-DVD LD;SOH-SBP2,SUS301,3.7,0.	1	SA
....5		AK61-01060A	HOLDER-LD BD;SOH-BP7,Zn,15.2,7.3,GRAY	1	SNA
....5		AK61-01061A	HOLDER-CL;SOH-BP7,PPS(FZ-3805 S2),27.0,1	1	SNA
....5		AK61-01073A	SPRING ETC-PBS DVD;SOH-BP7,SUS 304 0.15t	1	SNA
....5		AK61-01075A	SPRING ETC-DVD HOLDER;SOH-BP7,SUS 304,11	1	SNA

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
....5		AK61-01217A	SPRING ETC-CLD;BP7,sus304,0.10,1.5,1.7,1	1	SNA
....5		AK61-01257A	BASE-PICK UP;SOH-BP7VE,PPS(FZ-3805 S2),B	1	SNA
....5		AK61-01258A	HOLDER-LD/GT;SOH-BP7VE,Zn,6,8,6,GRAY	1	SNA
....5		AK63-00518A	COVER-FPCB;SOH-BP4,SUS304,T0.15,W3.2,L13	1	SNA
....5	SNA	AK63-00717A	COVER-BASE;SOH-BP7,STAINLESS-STS304,0.2t	1	SNA
....5		AK66-00202A	SHAFT-MAIN CLD;SOH-BP7,SUS304,25,1.2,SIL	1	SNA
....5		AK67-00044A	LENS-CL DVD;SOH-BP1,PLASTIC,NTR,PI5.2,1.	1	SNA
....5		AK67-00094A	LENS-BD GT;Grating,LENS,B270,None,3.0*2.	1	SNA
....5		AK67-00095A	LENS-PBS BD;SOH-BP5,GLS,WHT,6.2*5.0,1.5	1	SNA
....5		AK67-00110A	LENS-BD QWP;BD QWP,Plastic,WHT,4.0*4.0,0	1	SNA
....5	SNA	AK67-00130A	LENS-CD GT;BDP7 CD GT,LENS,B270,WHT,3.0*	1	SNA
....5		AK67-00131A	LENS-DVD PBS;BDP7 DVD PBS,LENS,B270,WHT,	1	SNA
....5		AK67-00132A	LENS-DVD MR;BDP7 DVD MR,LENS,B270,WHT,4.	1	SNA
....5		AK67-00133A	LENS-DVD PLATE;BDP7 DVD PLATE,LENS,B270,	1	SNA
....5		AK67-00134A	LENS-BD CL;BDP7 BD CL,Z340R,WHT,4.4*5.3,	1	SNA
....5		AK67-00135A	LENS-BD ASL;BDP7 BD ASL,Z340R,WHT,Pi 2.4	1	SNA
....5		AK67-00159A	LENS-BD MRR;BDP7 BD MRR,LENS,B270,WHT,6.	1	SNA
....5		AK96-01830A	ASSY PICK UP P-PCB;SOH-BP8	1	SNA
.....6		0202-001477	SOLDER-CREAM;LST309-M,D20~45um,96.5Sn/3A	0	SNA
.....6		0603-001257	PHOTO-RECEIVER;6V,650nm	1	SNA
.....6		0603-001259	PHOTO-RECEIVER;5.7V,405nm	1	SNA
.....6	R700	1404-001328	THERMISTOR-NTC;10Kohm,0A,3370K,0mW/C,0uF	1	SNA
.....6	R105	2007-000138	R-CHIP;100ohm,5%,1/16W,TP,1005	1	SA
.....6	R16	2007-001313	R-CHIP;330ohm,5%,1/16W,TP,1005	1	SA
.....6	HR10	2007-001320	R-CHIP;1.8Kohm,5%,1/16W,TP,1005	1	SA
.....6	ND51C2	2104-001087	VR-SMD;2.2Kohm,25%,0.15W,TOP	2	SNA
.....6	S.N.A	2104-001125	VR-SMD;1KOHM,25%,1/10W,TOP	1	SNA
.....6	VC37	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,1005	3	SA
.....6	AD480	2203-006399	C-CER,CHIP;1000nF,10%,6.3V,X5R,TP,1005	4	SA
.....6	S.N.A	3301-001808	BEAD-SMD;120ohm,1005,TP,530ohm/390MHz,12	4	SA
.....6	J1	3708-002203	CONNECTOR-FPC/FFC/PIC;40P,0.5mm,SMD-A,AU	1	SA
.....6		AK41-01105A	PCB MAIN;BDP8-Main,FR-4,2,2.1,0.6T,34.8	1	SNA
.....6		AK41-01107A	FPC-BD;BDP8-BD,1.0,POLYIMDE,20,0.075T	1	SNA
.....6		AK41-01108A	FPC-DVD;BDP8-DVD,1.0,POLYIMDE,20,0.075T	1	SNA
.....6		AK41-01109A	FPC-ACT;BDP8-ACT,1.0,POLYIMDE,6,0.075T	1	SNA
.....6		AK61-01248A	PLATE-PD BD;SOH-BP8,SPCC,2.15t,13,7.0,SI	1	SNA
.....6		AK61-01249A	PLATE-PD DVD;SOH-BP8,SPCC,1.65t,11.8,6.5	1	SNA
1		AK90-00216A	ASSY COVER BOTTOM;BD-E5500	1	SNA
.2		AK96-01894A	ASSY COVER P-BOT;BD-E8500,SECC T0.8	1	SNA
..3	EF01	3103-001290	FAN-DC;12 VDC,2200rpm,0.147m^3/mi,0.921m	1	SA

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
..3	W275	6003-001561	SCREW-TAPTYPE;BH,+,-,B,M3,L6,ZPC(WHT),SW	2	SA
..3	C1023	AK61-00608A	LEG;DVD-VR330,RUBBER,BLK,12	4	SNA
..3	RB01	AK63-00893A	COVER-BOTTOM;BD-E8900,EGI-SECC,0.8	1	SNA
..3		AK63-00895B	COVER-CI;BD-E8900,ABS+PMMA,1 CI CARD	1	SNA
..3		AK63-00939A	GASKET;BD-E8900,Conductive Fabric,15,22,	1	SNA
..3	CLAMP	AK65-00001A	CLAMPER CORE-CORD POWER;EXINO,ABS,BLK	1	SNA
...4		0103-004609	RESIN-ABS;HF-0680U,K21294,BK0007,1.5mm H	2	SNA
..3	M0131	GK63-00065A	GASKET;71TSFK 10-7-10-15,Conductive Fabr	1	SNA
1		AK90-00235A	ASSY COVER FRONT;BD-E8500	1	SNA
.2	F001A	AK96-01892A	ASSY COVER P-FRONT;BD-E8500,PMMA+ABS	1	SA
..3	W391	6003-000275	SCREW-TAPTYPE;BH,+,-,B,M3,L10,ZPC(BLK),SWR	3	SA
..3		AK01-00005A	FILM-ITO;NTP05TK-20,BD-D8700/BD-D6800,IT	1	SNA
..3		AK63-00838K	SHEET-PROTECTION FRONT;BD-E8500,PET,0.07	430	SNA
..3	F001	AK63-00894A	COVER-FRONT;BD-E8900,ABS+PMMA	1	SNA
...4		0103-007790	RESIN-ABS PMMA;SF-0505EH,G01153,BK0041,1	128	SNA
..3		AK63-00937A	GASKET;BD-E8900,Conductive Fabric,14,7,1	1	SNA
..3	FD12	AK64-02544A	DOOR-USB;BD-D5300,ABS,T2.0,H40,W50,L20,B	1	SA
..3		AK64-02554A	BADGE-BRAND;HT-E8200,ABS+PMMA,35	1	SNA
..3	MF01A	AK94-00540A	ASSY PCB FRONT;BD-E8900,ASSY PCB FRONT	1	SA
...4		0202-001463	SOLDER-WIRE;LFC2-W3.0,-,D3,99.79Sn/0.2Cu	1	SNA
...4		0204-002420	SOLVENT;1M-1000,C3H7OH,96	1	SNA
...4		0204-002607	FLUX;DF-234U,13%,14KG,Gravity 0.82	0	SNA
...4	RM701	0609-001202	MODULE REMOCON;HORIZONTAL,12.4mm,TR	1	SA
...4	EV01	AK07-00079A	VF DISPLAY;006BT356NK,BD-D8500(LEAD:9mm)	1	SA
...4	AH410	AK61-01252A	HOLDER-VFD;BD-E6700,ABS	1	SNA
....5		0103-004609	RESIN-ABS;HF-0680U,K21294,BK0007,1.5mm H	7	SNA
...4	AF020	AK63-00891A	FILTER-VFD;BD-E6700,PC,NTR	1	SA
....5		0103-009597	RESIN-PC;SC-1220R,50201,RD0045,V-2	5	SNA
...4	AS102	AK63-00927A	SHEET-POWER;BD-E6500,8500, HT-E6500,PC*,	1	SNA
...4		AK97-05094A	ASSY SMD;AK94-00540A	1	SNA
....5		0202-001477	SOLDER-CREAM;LST309-M,D20~45um,96.5Sn/3A	0	SNA
....5		0403-000489	DIODE-ZENER;MMSZ5228B,5%,500MW,SOD-123,T	1	SA
....5		0403-001779	DIODE-ZENER;MMSZ5234BT1G,5.89/6.51V,500m	1	SA
....5	D1103	0406-001239	DIODE-TVS;RClamp0502B,6/-V,125W,SOT-52	1	SA
....5		0406-001253	DIODE-TVS;VESD05A1-02V,6.0/6.8/7.5V,SOD-	2	SNA
....5	EL02	0601-002733	LED;SMD(TOP VIEW),WHT,3.5x2.8x1.8mm,3.5x	1	SA
....5		1003-002386	IC-VFD;PT6325,QFN,48P,6x6mm,-40 to 20mA,	1	SNA
....5	CER02	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....5	PR6	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	SNA
....5	AR30	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	2	SA

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
....5	R830	2007-000101	R-CHIP;82Kohm,5%,1/10W,TP,1608	1	SA
....5	ARR2	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	SA
....5	HDR7	2007-000139	R-CHIP;220ohm,5%,1/16W,TP,1005	5	SA
....5	R104	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	2	SA
....5	R338	2007-000173	R-CHIP;22ohm,5%,1/16W,TP,1005	3	SNA
....5	AR30	2007-001306	R-CHIP;150ohm,5%,1/16W,TP,1005	1	SA
....5	C254	2203-000438	C-CER,CHIP;1nF,10%,50V,X7R,TP,1005	1	SA
....5	AD480	2203-002285	C-CER,CHIP;10nF,10%,50V,X7R,TP,1005	2	SNA
....5	VC37	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,1005	1	SA
....5	AD480	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,TP,3216	1	SA
....5	HDC11	2203-006562	C-CER,CHIP;1000nF,10%,10V,X5R,TP,1005	3	SA
....5	AD480	2203-007513	C-CER,CHIP;10000nF,10%,10V,X5R,TP,1608,0	1	SA
....5	T0568	3301-002039	BEAD-SMD;26ohm,1608,TP	1	SA
....5		3601-001376	FUSE-SURFACE MOUNT;32V,3A,FAST-ACTING,Hi	1	SNA
....5	AC510	3708-001618	CONNECTOR-FPC/FFC/PIC;5P,1mm,SMD-A,Sn-Pb	1	SA
....5	CN353	3708-002555	CONNECTOR-FPC/FFC/PIC;22P,1mm,SMD-A,SN,N	1	SNA
....5	AC510	3708-002624	CONNECTOR-FPC/FFC/PIC;8P,0.5mm,SMD-A,AU,	1	SA
....5		AK11-00021A	IC MASK ROM-TOUCH SENSOR;TOUCHCORE350-ML	1	SNA
....5		AK41-01134A	PCB-VFD;BD-E8900,CEM-3,2,00,1.6T,238.5 x	1	SNA
...3		AK94-00541A	ASSY PCB S-USB;BD-E8900,ASSY SUB-USB	1	SA
...4	CN161	3708-002161	CONNECTOR-FPC/FFC/PIC;5P,1mm,ANGLE,SN,N,	1	SA
...4	CN2	3722-002313	JACK-USB;4P/1C,AU30U,BLK,STRAIGHT,A TYPE	1	SA
...4		AK41-01137A	PCB-USB;BD-E8900,FR-1,1,00,1.6T,151.5 x	1	SNA
...3	FL06	AK96-01943H	ASSY CABLE P-FFC;BD-E8900,FFC,SJ11-01-41	1	SA
...3	FL06	AK96-01943K	ASSY CABLE P-FFC;BD-E8900,FFC,SJ11-01-45	1	SA
1		AK91-01136B	ASSY SHIELD;BD-E8500	1	SNA
.2	P025	3903-000176	CBF-POWER CORD;AT,EU,CP2,HOUSING(2P),250	1	SA
.2	W336	6001-000742	SCREW-INCH MACH;PH,+,UNC6-32,L4.2,ZPC(WH	4	SA
.2	W391	6003-000275	SCREW-TAPTYPE;BH,+,B,M3,L10,ZPC(BLK),SWR	5	SA
.2	M0081	6003-001375	SCREW-TAPTYPE;BH,+,-,B,M3,L8,ZPC(WHT),SW	13	SA
.2		AK39-00168A	LEAD CONNECTOR-SATA CABLE;BD-E8900,S-ATA	1	SA
.2		AK61-00916A	GUIDE-SPECIAL;DVD-SH895,M3 TAPTITE,3,8,1	4	SNA
.2		AK68-02223D	LABEL-POP TRANSPARANT STICKER;BD-E8500/Z	1	SNA
.2	T001A	AK96-01893A	ASSY COVER P-TOP;BD-E8500,PMMA+ABS	1	SA
...3		AH63-02605B	SHEET-INSULATOR;BDP-E8900,PC,0.5,88.0,17	1	SNA
...3		AK63-00838L	SHEET-PROTECTION TOP;BD-E8500,PET,0.07,W	430	SNA
...3	T001	AK63-00896A	COVER-TOP;BD-E8900,ABS+PMMA,HB	1	SNA
...4		0103-005096	RESIN-ABS;HAM 8560,98055,2.0mm HB	510	SNA
.2	FL06	AK96-01943J	ASSY CABLE P-FFC;BD-E8900,FFC,SJ11-01-45	1	SA
.2	P295	AK97-02472A	ASSY BRACKET-HDD;HDD,DVD-SH895/XEF,09-HD	1	SNA

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
..3	VS074	AK61-00914A	BRACKET-HDD;DVD-SH895,SECC,T0.8,130,104.	1	SNA
..3	C701	AK73-00028A	RUBBER-HDD;DVD-HR800/XAA,BUTHYL 40Hs,10*	4	SNA
.2	M0131	BN63-00209A	GASKET;RS24NS,Conductive Fabric,4mm,10mm	1	SNA
.2		BP63-00367C	GASKET-TAPE;SVP-50L7HX,Conductive Fabric	1	SNA
1	M0017	AK91-01151A	ASSY CHASSIS;BD-E8300/ZF,ASSY CHASSIS	1	SNA
.2		AK59-00138A	NETWORK-WLAN MODULE;DNUB-S234B,BCM43234B	1	SA
.2	P001A	AK94-00513A	ASSY PCB SMPS;BD-E8500,XF,SMPS ASSY,1L	1	SA
..3	D1S40	0402-000351	DIODE-RECTIFIER;1N4937,600V,1A,DO-41,TP	1	SA
..3	BD01	0402-001608	DIODE-BRIDGE;GBJ2J,600V,2A,SIP-4,BK	1	SA
..3	D1SS16	0402-001680	DIODE-RECTIFIER;SF34,200V,3A,DO-201AD,TP	2	SA
..3		0404-001609	DIODE-SCHOTTKY;MBRF20U200CT,200V,20000mA	2	SA
..3		0604-001466	PHOTO-COUPLER;TR,130~260,250mW,DIP-4,ST	1	SA
..3	IC1P02	1203-002183	IC-SWITCH VOL. REG.;278R12,TO-220F-4L,4P	1	SA
..3		1203-006227	IC-PWM CONTROLLER;ICE3BR1065JF,TO-220F(6	1	SNA
..3	PRF10	1404-001361	THERMISTOR-NTC;3ohm,4A,-,35mW/C,0uF,9,TP	1	SA
..3		1405-000152	VARISTOR;560V,455Vdc,2500A,14x8.5mm,TP,9	2	SA
..3	PCD02	2201-000963	C-CERAMIC,DISC;1nF,20%,400V,Y5U,9.5x6mm,	1	SA
..3	C01	2201-002044	C-CERAMIC,DISC;0.1nF,10%,400V,Y5P,8.5x6mm	1	SA
..3	PCF01	2301-001683	C-FILM,MPEF;100nF,20%,275V,BK,12.5x6x12mm	2	SA
..3	C1S31	2401-000717	C-AL;2200uF,20%,25V,WT,TP,12.5x25,5	1	SNA
..3	C	2401-004052	C-AL;2200UF,20%,16V,-,TP,12.5X25,5	3	SA
..3		2401-004934	C-AL;68uF,20%,450V,BK,18*25,7.5mm	1	SA
..3	F1P01	3601-001127	FUSE-RADIAL LEAD;250V,3.15A,TIME-LAG,PVC	1	SA
..3	H008	3710-001919	SOCKET-BOARD TO CABLE;16P,1R,2.5mm,ANGLE	1	SA
..3	PCNS2	3711-000203	HEADER-BOARD TO CABLE;1WALL,2P/3P,1R,7.9	1	SA
..3	HB01A	3711-004270	HEADER-BOARD TO CABLE;BOX,2P,1R,2mm,ANGL	1	SA
..3	DRVCM	3711-004379	HEADER-BOARD TO CABLE;BOX,4P,1R,2mm,STRA	1	SA
..3		AH26-00388A	TRANS SWITCHING;BD-E8500 7900,Free,PL7,P	1	SA
..3	T0010	AK27-00008A	COIL CHOKE;BAR5*20,BD-P1600,5.5uH,25%,0.	1	SA
..3		AK29-00006B	FILTER LINE NOISE;BD-C6900,UU1116V,2.46o	2	SA
..3		AK97-04973A	ASSY AUTO;XF,1L,AK94-00513A	1	SNA
...4	PDS11	0402-000012	DIODE-RECTIFIER;UF4007,1000V,1A,DO-41,TP	1	SA
...4	D1S40	0402-000351	DIODE-RECTIFIER;1N4937,600V,1A,DO-41,TP	2	SA
...4	PZD22	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57/9.01V,500mW,DO	1	SA
...4	PZD21	0403-000752	DIODE-ZENER;MTZJ22C,21.08-22.17V,500MW,D	1	SA
...4		0403-000754	DIODE-ZENER;MTZJ30C,28.2-29.6V,500mW,DO-	1	SA
...4	IC012	1203-001217	IC-POS.LADJUST REG.;431,TO-92,3P,4.58MIL	1	SA
...4	R3A04	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2mm	1	SA
...4	R1P10B	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	1	SA
...4	VR5	2001-000325	R-CARBON;120ohm,5%,1/8W,AA,TP,1.8x3.2mm	1	SA

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
...4	SCR3	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	1	SA
...4	PRS31	2001-000440	R-CARBON;1ohm,5%,1/8W,AA,TP,1.8x3.2mm	1	SA
...4	R1SF14	2001-000527	R-CARBON;22ohm,5%,1/8W,AA,TP,1.8x3.2mm	2	SA
...4	PRF01	2002-000121	R-COMPOSITION;1Mohm,10%,1/2W,AA,TP,3.5x9	1	SA
...4		2003-000403	R-METAL OXIDE(S);0.68ohm,5%,2W,AF,TP,3.9	1	SC
...4		2003-002102	R-METAL OXIDE(S);68Kohm,5%,2W,AF,TP,4x12	1	SC
...4		2003-002454	R-METAL OXIDE;0.22ohm,5%,1W,AF,TP,3.8x10	1	SA
...4		2004-000202	R-METAL;100ohm,1%,1/8W,AA,TP,1.8x3.2mm	1	SNA
...4	PRS33	2004-000433	R-METAL;1Kohm,1%,1/8W,AA,TP,1.8x3.2mm	1	SA
...4	R1SS34	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	1	SA
...4	PCD12	2201-002076	C-CERAMIC,DISC;0.068nF,10%,1000V,SL,-,8x	1	SA
...4	PCS32	2301-000129	C-FILM,LEAD-PEF;100nF,5%,50V,TP,10x9x4.3	1	SC
...4	C1S17	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	1	SA
...4	C1S11	2301-000402	C-FILM,LEAD-PEF;1nF,5%,50V,TP,6x9.5x3.5m	2	SNA
...4	PCD11	2305-001029	C-FILM,LEAD-PEF;10nF,10%,630V,TP,12x9x12	1	SA
...4	C	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	1	SA
...4	C1P102	2401-001583	C-AL;47uF,20%,50V,WT,TP,6.3x11,5	3	SC
...4	C	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	1	SA
...4	C1S38	2401-003499	C-AL;330uF,20%,16V,LZ,TP,8x11.5mm,5	1	SA
...4		2401-005161	C-AL;0.47uF,20%,50V,TP,5*11,5mm	1	SA
...4	BD707	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,-,TP,-,-,	1	SNA
...4	JP21	3811-001868	WIRE-NO SHEATH CU;SnCuFe,52mm,GRY	8	SNA
...4	PBS01	AC27-92001M	COIL-INDUCTOR;RH3.5x6.5RS,BEAD(RADIAL),T	1	SC
...4		AK41-01115B	PCB-SMPS;BD-E8500 E7900,CEM-1,1L,00,1.6,	1	SNA
.2		AK94-00567A	ASSY PCB S-HDD;BD-E8900,ZF,320GB	1	SNA
...3	EH01	AK59-00107A	HDD;320G,ST3320311CS,63/track,16,16,383,	1	SA
.2	M0014	AK94-00571A	ASSY PCB MAIN;BD-E8300/ZF,MAIN PCB ASSY	1	SA
...3		0202-001463	SOLDER-WIRE;LFC2-W3.0,-,D3,99.79Sn/0.2Cu	4	SNA
...3		0204-002420	SOLVENT;1M-1000,C3H7OH,96	5	SNA
...3		0204-002607	FLUX;DF-234U,13%,14KG,Gravity 0.82	3	SNA
...3		3709-001670	CONNECTOR-CARD SLOT;68P,1.27mm,stmap,AU,	1	SA
...3		3711-008135	HEADER-BOARD TO BOARD;NOWALL,16P,1R,2.5m	1	SA
...3		3722-003397	JACK-MODULAR;8P/8C,Yes,ANGLE-DIP,W/O,AU,	1	SA
...3		3722-003407	JACK-PIN;3P+SPDIF,NI+SN,RED/YEL/WHT,ANGL	1	SA
...3	ET01	AK40-00048A	TUNER;DTCQ-11X2NS/C3-D5,DTCQ-11X2NS/C3-D	1	SA
...3		AK62-00056A	HEAT SINK-ES;BD-E8900,A6063,BLACK,56*46*	1	SNA
...3		AK97-05143J	ASSY DRM;BD-E8500	1	SNA
...4		BN46-00109H	KEY CODE-CERTIFI;MAC,TV/AV,General	1	SNA
...4		BN46-00215J	KEY CODE;PACK,AV,EchoB,BD-E8900	1	SNA
...4		BN46-00216A	KEY CODE-CERTIFI;CI+,AV,EchoB,BD-E8900	1	SNA

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
...3		AK97-05272A	ASSY SMD;BD-E8300/ZF,MAIN PCB ASSY,AK94-	1	SNA
...4		0202-001477	SOLDER-CREAM;LST309-M,D20~45um,96.5Sn/3A	4	SNA
...4	DS01A	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	SA
...4	D1103	0406-001239	DIODE-TVS;RClamp0502B,6/-/-V,125W,SOT-52	10	SA
...4		0406-001395	DIODE-TVS;AOZ8802ADI,6/-/-V,DFN-6	1	SA
...4	Q1040	0501-000457	TR-SMALL SIGNAL;MMBT2222A/KST2222A,NPN,3	1	SA
...4	Q1042	0501-000462	TR-SMALL SIGNAL;MMBT2907A,PNP,350mW,SOT-	3	SA
...4	Q613	0501-000465	TR-SMALL SIGNAL;MMBT3904,NPN,350mW,SOT-2	3	SA
...4	Q601	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47Kohm,	1	SA
...4	AQ8	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	1	SA
...4		0505-001377	FET-SILICON;BSN20,N,50V,100mA,15ohm,250W	1	SA
...4		0505-002598	FET-SILICON;AP2317GN,P,-20V,-4.2A,0.052o	2	SA
...4	IC104	0801-002095	IC-CMOS LOGIC;74LCX245,TRANSCEIVER,TSSOP	1	SA
...4	IC104	0801-002172	IC-CMOS LOGIC;74LCX16244,BUFFER/LINE DRI	1	SA
...4	IC104	0801-002630	IC-CMOS LOGIC;74AHCT1G08,2-INPUT AND GAT	1	SA
...4	ND51C2	0801-002780	IC-CMOS LOGIC;74LVC1G17,SCHMITT-TRIGGER	2	SNA
...4		0903-001771	IC-MICROCONTROLLER;LQFP (EPAD),128P,14 m	1	SA
...4		1002-001662	IC-D/A CONVERTER;PCM5101,24,TSSOP,20P,6.	1	SA
...4		1003-002383	IC-MOTOR DRIVER;TPIC1391DBTRG4,TSSOP,30P	1	SNA
...4		1003-002384	IC-MOTOR DRIVER;TPIC1407,DFD,56P,14.10x6	1	SNA
...4	IC112	1103-001310	IC-EEPROM;24LC02B,256X8BIT,SOIC,8P,3.91X	1	SNA
...4		1103-001506	IC-EEPROM;M24512-RMN6TP,512Kbit,64Kx8,SO	1	SA
...4		1105-002269	IC-DDR3 SDRAM;K4B2G1646C-HCMA,DDR3 1866,	2	SA
...4		1105-002274	IC-DDR3 SDRAM;K4B1G1646G-BCMA,DDR3 1866,	2	SNA
...4		1201-003331	IC-VIDEO AMP;MM1756DURE,TSOP,6P,2x1.25mm	1	SNA
...4		1203-004363	IC-VOL. DETECTOR;RT9818C-29PV,SOT-23,3P,	1	SA
...4		1203-006067	IC-POWER SUPERVISOR;TPS2553DBVR,SOT-23,6	3	SNA
...4	IC012	1203-006239	IC-POS1.ADJUST REG.;AP1117EGZ-13-89,SOT-	1	SA
...4		1203-006606	IC-DC/DC CONVERTER;AOZ1036PI,SO-8,8P,4.8	1	SNA
...4		1203-007005	IC-POS1.FIXED REG.;G912F11U,SOP-8(FD),8P	1	SA
...4		1203-007080	IC-DC/DC CONVERTER;AOZ1051PI,SO-8,8P,4.9	3	SA
...4		1203-007246	IC-POS1.FIXED REG.;AP7361-18Y-13,SOT89-5	1	SA
...4		1204-003316	IC-VIDEO DECODER;SDP1105,732P,27x27x2.2m	1	SA
...4		1205-003834	IC-ETHERNET CONTROLLER;RTL8201E-VC-GRT,Q	1	SA
...4		1205-004447	IC-SWITCH;TPS2051CDBVR,SOT23-5,5P,3x1.65	1	SA
...4		1301-002056	IC-CPLD;5M40ZE64C5N,EQFP,64P,9x9mm,0to+8	1	SNA
...4	HD9	1405-001192	VARISTOR;12Vdc,30A,1.6x0.8x0.55mm,TP,50V	3	SA
...4	J914	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	1	SC
...4		2007-000039	R-CHIP;0ohm,1%,1/10W,TP,1608	2	SA
...4	PR4	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	2	SA

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
...4	ND51C2	2007-000066	R-CHIP;20Kohm,1%,1/10W,TP,1608	1	SNA
...4	AR30	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	2	SA
...4	AR150	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	7	SA
...4	R830	2007-000101	R-CHIP;82Kohm,5%,1/10W,TP,1608	2	SA
...4	R309	2007-000105	R-CHIP;200Kohm,5%,1/10W,TP,1608	1	SNA
...4	R510	2007-000108	R-CHIP;510Kohm,5%,1/10W,TP,1608	1	SA
...4	AAR39	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	2	SA
...4	R1053	2007-000131	R-CHIP;91Kohm,5%,1/10W,TP,1608	1	SA
...4	R105	2007-000138	R-CHIP;100ohm,5%,1/16W,TP,1005	20	SA
...4	HDR7	2007-000139	R-CHIP;220ohm,5%,1/16W,TP,1005	1	SA
...4	AR49	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	15	SA
...4	MR306	2007-000141	R-CHIP;2.2Kohm,5%,1/16W,TP,1005	2	SA
...4	R319	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP,1005	20	SA
...4		2007-000146	R-CHIP;6.8Kohm,5%,1/16W,TP,1005	2	SA
...4	R104	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	53	SA
...4	MR13	2007-000157	R-CHIP;47Kohm,5%,1/16W,TP,1005	9	SA
...4	DR39	2007-000162	R-CHIP;100Kohm,5%,1/16W,TP,1005	1	SA
...4	MR16	2007-000168	R-CHIP;470Kohm,5%,1/16W,TP,1005	1	SNA
...4	R111	2007-000171	R-CHIP;0ohm,5%,1/16W,TP,1005	26	SNA
...4	R157	2007-000208	R-CHIP;1.1Kohm,1%,1/10W,TP,1608	1	SA
...4	VR8	2007-000256	R-CHIP;1.6Kohm,1%,1/10W,TP,1608	1	SA
...4	WR18B	2007-000463	R-CHIP;18ohm,5%,1/10W,TP,1608	2	SA
...4	R1S36	2007-000491	R-CHIP;2.2Kohm,1%,1/10W,TP,1608	1	SA
...4	MR8	2007-000503	R-CHIP;2.2ohm,5%,1/10W,TP,1608	1	SA
...4	UR16	2007-000552	R-CHIP;20ohm,5%,1/10W,TP,1608	2	SA
...4	R3A05	2007-000616	R-CHIP;24Kohm,5%,1/10W,TP,1608	2	SA
...4	PR2	2007-000651	R-CHIP;27Kohm,1%,1/10W,TP,1608	1	SA
...4	AR28	2007-000683	R-CHIP;3.3Kohm,1%,1/10W,TP,1608	1	SA
...4		2007-000736	R-CHIP;30Kohm,1%,1/10W,TP,1608	1	SA
...4	R124	2007-000775	R-CHIP;33Kohm,5%,1/16W,TP,1005	4	SNA
...4	RF03	2007-000828	R-CHIP;39Kohm,1%,1/10W,TP,1608	1	SA
...4	R980	2007-000929	R-CHIP;470ohm,1%,1/10W,TP,1608	2	SNA
...4	ZRA4	2007-000931	R-CHIP;470ohm,5%,1/8W,TP,2012	1	SNA
...4	R858	2007-001007	R-CHIP;51Kohm,1%,1/10W,TP,1608	1	SA
...4	AR132	2007-001010	R-CHIP;51Kohm,5%,1/10W,TP,1608	1	SA
...4	R703	2007-001153	R-CHIP;750ohm,1%,1/10W,TP,1608	1	SA
...4	ZR10	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	SA
...4	OTR1	2007-001292	R-CHIP;33ohm,5%,1/16W,TP,1005	150	SA
...4	DR43	2007-001298	R-CHIP;51ohm,5%,1/16W,TP,1005	1	SNA
...4		2007-001319	R-CHIP;1.2Kohm,5%,1/16W,TP,1005	1	SA

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
...4		2007-001329	R-CHIP;7.5Kohm,5%,1/16W,TP,1005	1	SA
...4		2007-001342	R-CHIP;2Mohm,5%,1/10W,TP,1608	1	SA
...4	R3301	2007-001433	R-CHIP;12Kohm,1%,1/10W,TP,1608	2	SA
...4	R1	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	12	SNA
...4		2007-007008	R-CHIP;300ohm,5%,1/16W,TP,1005	1	SA
...4	DR4	2007-007142	R-CHIP;10Kohm,1%,1/16W,TP,1005	18	SA
...4		2007-007306	R-CHIP;100ohm,1%,1/16W,TP,1005	4	SNA
...4		2007-007318	R-CHIP;1Kohm,1%,1/16W,TP,1005	14	SNA
...4		2007-007517	R-CHIP;240ohm,1%,1/16W,TP,1005	6	SNA
...4		2007-007538	R-CHIP;56Kohm,1%,1/16W,TP,1005	2	SA
...4		2007-007588	R-CHIP;1.8Kohm,1%,1/16W,TP,1005	1	SA
...4		2007-007617	R-CHIP;2.49Kohm,1%,1/10W,TP,1608	1	SA
...4	R133	2007-007651	R-CHIP;9.1Kohm,1%,1/10W,TP,1608	1	SA
...4		2007-007766	R-CHIP;2Kohm,1%,1/16W,TP,1005	9	SA
...4		2007-007767	R-CHIP;200ohm,1%,1/16W,TP,1005	3	SA
...4		2007-007834	R-CHIP;16.5Kohm,1%,1/10W,TP,1608	2	SA
...4		2007-008070	R-CHIP;130ohm,1%,1/10W,TP,1608	1	SNA
...4		2007-008213	R-CHIP;4.3Kohm,1%,1/16W,TP,1005	2	SNA
...4		2007-008263	R-CHIP;3Kohm,1%,1/16W,TP,1005	1	SA
...4		2007-008391	R-CHIP;6.34Kohm,1%,1/16W,TP,1005	1	SA
...4	DC30	2203-000138	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1005	4	SA
...4	PC43	2203-000233	C-CER,CHIP;0.1nF,5%,50V,C0G,TP,1005	1	SA
...4	DC54	2203-000278	C-CER,CHIP;0.01nF,0.5pF,50V,C0G,TP,1005	2	SA
...4	DC93	2203-000311	C-CER,CHIP;0.12nF,5%,50V,C0G,TP,1005	6	SA
...4	DC2	2203-000330	C-CER,CHIP;0.012nF,5%,50V,C0G,TP,1005	2	SA
...4	DC1	2203-000386	C-CER,CHIP;0.015nF,5%,50V,C0G,TP,1005	3	SA
...4	C254	2203-000438	C-CER,CHIP;1nF,10%,50V,X7R,TP,1005	3	SA
...4	C507	2203-000489	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1005	4	SA
...4	AD480	2203-000679	C-CER,CHIP;0.027nF,5%,50V,C0G,TP,1005	2	SA
...4	AD480	2203-000714	C-CER,CHIP;3.3nF,10%,50V,X7R,TP,1005	5	SA
...4	AC35	2203-001239	C-CER,CHIP;0.082nF,5%,50V,NP0,TP,1005	3	SNA
...4	AD480	2203-002285	C-CER,CHIP;10nF,10%,50V,X7R,TP,1005	19	SNA
...4	AAC1	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,1608	10	SA
...4	AD480	2203-005511	C-CER,CHIP;27nF,10%,10V,X7R,TP,1005	1	SA
...4	AD480	2203-005968	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1005,0.5	2	SNA
...4	C239	2203-006047	C-CER,CHIP;33nF,10%,16V,X7R,TP,1005	2	SA
...4	VC37	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,1005	283	SA
...4	C102	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,TP,1005,0.5	3	SA
...4	C510	2203-006170	C-CER,CHIP;220nF,10%,16V,X7R,TP,1608	1	SA
...4	JC10	2203-006324	C-CER,CHIP;2200nF,10%,10V,X5R,TP,1608	2	SA

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
...4	C802	2203-006348	C-CER,CHIP;1000nF,10%,25V,X5R,TP,1608,0.	7	SA
...4	C125	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2012	33	SC
...4	HE4	2203-006474	C-CER,CHIP;22000nF,20%,6.3V,X5R,TP,2012	15	SA
...4	HDC11	2203-006562	C-CER,CHIP;1000nF,10%,10V,X5R,TP,1005	10	SA
...4	AD480	2203-006824	C-CER,CHIP;4700nF,10%,10V,X5R,TP,1608	2	SNA
...4	C23	2203-006890	C-CER,CHIP;10000nF,20%,6.3V,X5R,TP,1608	30	SA
...4	AD480	2203-007176	C-CER,CHIP;10000nF,10%,16V,X5R,TP,2012,1	4	SNA
...4	AD480	2203-007306	C-CER,CHIP;10000nF,10%,25V,X5R,TP,2012,1	6	SNA
...4	T0052	2703-003149	INDUCTOR-SMD;2.2uH,20%,5050	1	SA
...4	T0052	2703-003790	INDUCTOR-SMD;4.7uH,20%,8080	2	SA
...4		2703-003930	INDUCTOR-SMD;4.7uH,20%,5050	1	SA
...4	CF2	2801-004655	CRYSTAL-SMD;25MHz,50ppm,SX-3,18pF,25ohm,	1	SA
...4		2801-004913	CRYSTAL-SMD;24MHz,10ppm,SX-1,12pF,30ohm,	1	SNA
...4		2801-004932	CRYSTAL-SMD;25MHz,30ppm,SMD,12pF,40ohm,T	1	SA
...4		2801-005146	CRYSTAL-SMD;20MHz,30ppm,SX-1,10pF,30ohm,	1	SNA
...4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz,-	10	SA
...4	T0568	3301-002039	BEAD-SMD;26ohm,1608,TP	17	SA
...4	F201	3601-001374	FUSE-SURFACE MOUNT;32V,5A,FAST-ACTING,PL	1	SA
...4		3701-001792	CONNECTOR-HDMI;19P,2ROW,FEMALE,ANGLE,AU	1	SA
...4	AC510	3708-001837	CONNECTOR-FPC/FFC/PIC;15P,1mm,SMD-S,SN,N	1	SA
...4	AC510	3708-002140	CONNECTOR-FPC/FFC/PIC;5P,1mm,SMD-S,SnPb,	1	SA
...4	AC510	3708-002603	CONNECTOR-FPC/FFC/PIC;22P,1mm,SMD-S,SN,N	1	SNA
...4		3708-002908	CONNECTOR-FPC/FFC/PIC;40P,0.5mm,SMD-S,0.	1	SA
...4	CN906	3711-006947	CONNECTOR-HEADER;1WALL,7P,1R,1.27mm,STRA	1	SNA
...4		AK41-01131A	PCB MAIN;BD-E8900,FR-4,4,00,1.2,142 x 23	1	SNA
...4		AK97-05088A	ASSY MICOM;BD-E8900/ZF,MAIN PCB ASSY,AK9	1	SNA
....5		0903-001778	IC-MICROCONTROLLER;48P,7X7,20MHz,TR,PLAS	1	SNA
...4		AK97-05259A	ASSY MICOM-FLASH;BD-E8900	1	SNA
....5		1107-002088	IC-NAND FLASH;KLM2G1HE3F-B001,2GByte,16G	1	SNA
...4		AK97-05428A	ASSY MICOM-LOADER;BD-E8900	1	SNA
....5		1107-001916	IC-NOR FLASH;W25Q16BVSSIG,16Mbit,2Mbitx8	1	SNA
1	ACCE1	AK92-02236U	ASSY ACCESSORY;BD-E8900/ZF	1	SNA
.2	REMO2	AK59-00139A	REMOCON;TM1251,55Key,3V,PVR, BD-E8900, E	1	SA
.2		AK96-01939B	ASSY MANUAL P;BD-E8900,I/B,CARD,ZF	1	SNA
..3	T0524	6902-000286	BAG PE;LDPE,T0.03,W200,L300,TRP,28,2	1	SNA
..3		AK68-02230C	MANUAL USERS;BD-E8900,ZF,FRA,ITA,ES,POR,	1	SNA
.2	ACCE	AK97-01076A	ASSY ACCESSORY;DVD-R100E,-,SORT ACCESSOR	1	SNA
..3	BAG	6902-000031	BAG ZIPPER;LDPE,T0.05,W80,L160,TRP,0,0,4	1	SNA
..3	ACCE	AC39-00017A	CABLE-ETC-RF(PAL);SV-623X	1	SC
..3	C-A/V	AC39-42001R	CABLE-A/V;PVC	1	SC

Level	Location	Part Code	Description & Specification	Qty.	SA/SNA
..3	BATTERY	RAC43-12002H	BATTERY-DRY;Li-ion Polymer,4.2V,R03(AAAM	2	SNA
1		AK92-02238U	ASSY LABEL;BD-E8300/ZF	1	SNA
.2		AK68-01986B	LABEL RATING-01;BD-D,WW,PET 0.05,50,23.5	1	SNA
.2		AK68-02221N	LABEL-POP STAND;BD-E8300/ZF,SEF,ART PAPE	1	SNA
1		AK92-02255B	ASSY BOX;BD-E8500	1	SNA
.2		AH68-01981M	LABEL-BOX;ALL MODEL,ALL BUYER,heat sensi	1	SNA
.2		AK69-01062N	BOX-SET;BD-E8300/ZF,CB,SW2,A-1TYPE, OFFS	1	SNA
1		AK92-02257A	ASSY P/MATERIAL;BD-E8500	1	SNA
.2		AK63-00435B	SHEET-NITRON;BD-C5300/XAA,NITRON,0.5,630	1	SNA
.2		AK69-01056A	CUSHION-SET;BD-E8900,EPS,16.7g/l	1	SNA
.2		AK69-01056C	CUSHION-MIDDLE;BD-E8900,EPS	1	SNA
.2	T0527	BH68-40364A	LABEL-SUMMARY;G52,G72,ART,100G,WHT,BLK,W	1	SNA
.2		BN63-08890S	COVER-SHEET NITRON;LE37D550,PE,T2.0,1190	1	SNA
.2		BN63-09096A	COVER-PALLET FOIL;32D550,PE,T0.03,2000,2	1	SNA
.2	T0527	BN68-00129A	LABEL SHIPPING-00;LABEL SHIPPING,ART-PAP	1	SNA
.2		BN69-00257B	PACKING-PAD;- ,PAPER,-,-,CB-SW4,1100,790,	1	SNA
.2		BN69-05499A	PAD PACKING-EDGE;CB,T5,W50x50,L2300,YEL,	1	SNA
.2		BN69-05519A	PALLET-WOODEN;BN69-01058X,WOOD-OTH,1180,	1	SNA
.2		BN69-05929A	WRAP STRETCH FILM;All,LDPE,0.0066,440,42	1	SNA
.2		BN81-02321A	BAG-AIR;LIGHT FLEX PLASTIK,PE WHITE,L120	1	SNA
.2		HA83-00057B	LP-TAPE-CELLULOSE;;HA02-030010,T0,046,W7	1	SNA